

## 3000 Series DMX Control Console

The 3000 series of consoles is the perfect economical choice in lighting control product when a basic feature set is required. Offering either 4 or 8 channels of control, scene memory, and several chase options, these features provide easy lighting effects at the touch of a button. The 3000 series of consoles are designed to be easy to operate—many of the most often used features are documented on the bottom of the console. Connector pin outs are permanently screened next to the connector. When basic economical control is required, the 3000 series is the perfect choice.

### APPLICATIONS

- Elementary School
- Small Bands
- Church
- Any lighting control system with up to 4 or 8 control zones

### FEATURES

- DMX512 output
- 4 or 8 dimming control channels
- 4 or 8 recordable scene memory
- Chaser functions:
  - (2) selectable chases
  - Channel chase
  - Scene chase
  - Speed control
  - Direction control
  - Audio input
- Bump buttons for each channel or scene
- Master output fader



3008 model shown

### SPECIFICATIONS

- Power Supply: +100 – 240VAC “wall wart”
- Control Signal: DMX512-A
- Connector: 3-pin or 5-pin female XLR
- Audio Input: Maximum input: -10 db 100mV
- Dimensions (W x H x D): 9.13 in (232 mm) x 6.70 in (170 mm) x 2.20 in (56 mm)
- Weight: 2.4 lbs (1.2 kg)
- Shipping Weight: N3004 – 3.0 lbs (1.5 kg), N3008 – 3.36 lbs (1.18 kg)

### ORDERING INFORMATION

Cat. No.	Description
N3004-00D	4 Channel DMX Control Console
N3008-00D	8 Channel DMX Control Console