



Compatibility Guide

**for Headsets
and Telephones**

Blank Page

Using the Compatibility Guide

Use this list to determine which Plantronics headset models work with different telephone systems and their telsets.

1. Locate the telephone **Manufacturer**.
Manufacturers are listed in alphabetical order. **ALCATEL/ITT/CORTELCO**
2. Locate the telephone **System**. **64/144 PBX**
Alcatel 100:
3. Locate the specific telephone **Telset** model.

901 (PQS-7400)		M5
903 (PQS-7403)		"
904 (PQS-7402)		"
DSS Unit (PQS-7420)		NO
4. Look to the right to find the compatible **Headset** group(s) and proper switch settings.

M1 = M10 / M12 on switch position 1	P10 = Standard plug finger amplifier
M5 = M10 / M12 on switch position 5 with batteries installed.	P10H = High gain plug finger amplifier
J1 = JSB180-1 with P10	NO = Not compatible

If a small letter ^(a) appears, refer to the end of the section for that manufacturer for an explanation.

5. CA/CS 10 Switch settings:

CA/CS 10 on switch position 1-B equals **M10/M12** on switch position 1 (Carbon Phones)

CA/CS 10 not compatible with Comdial Impact or Siemens Dyad and Jr-Dyad Phones, 47521-01 cord required for use on phones with an **M2** setting.

CA/CS 10 on switch position 2-B equals **M10/M12** on switch position 5 (Electret Phones).

CA/CS 10 on switch position 1, 2 or 3-A are for **GE 2-9450** Phones.

6. S10 Switch settings:

S10 on position 1 equals **M10/M12** on switch position 1,3,4 and 5.

S10 on position 2 equals Definity phones - no **M10/M12** equivalent.

S10 on position 3 equals **M10/M12** on switch position 2.

S10 on position 4 equals GE 2-9450 phones - no **M10/M12** equivalent.

S10 on position 5 equals Siemens phones - no **M10/M12** equivalent.

S10 on position 6 equals N. W. Bell phones - no **M10/M12** equivalent.

The **S10** is compatible with the same phones as an **M10/M12**.

7. Refer to Appendix A, *Guide to Special Headset Groups* for a listing of all Plantronics headsets within each Headset Group.

8. Refer to Appendix B, *Cross Reference Chart* to cross reference old product/groups with new technology.

9. Refer to Appendix C, *SP05/PLX500 Compatibility Information*.

This list represents Plantronics best effort to match our headsets with the growing number and variety of telephones on the market. It will be revised as more compatibility information is obtained. Plantronics disclaims all responsibility for omissions and errors. For compatibility questions not answered in this list, call Plantronics at 1-800-544-4660.

Blank Page

ADC TELECOMMUNICATIONS

ADC Test Board **P10**

ALCATEL/ITT/CORTELCO

64/144 PBX

Alcatel 100:
901 (PQS-7400) **M5**
903 (PQS-7403) **"**
904 (PQS-7402) **"**
DSS Unit (PQS-7420) **NO**

3100

3100 Sets: **M5**
2630, 2672, 2673, 2872, 2873 **"**

3100XL

3100XL Sets: **M5**
281175, 281075, 281975 **"**
281575, 282175, 282075 **"**
282975, 282575 **"**
3100 Console: **"**
237501 TLP, TSP **"**

2300

Telset **M5**

EKS 401/701

EKS 401, 616, 701, 2701 **M1**

801, 802

EKS 801/802 Sets: **M5**
2801, 2802, 2803 **"**
2804, 2805, 2806 **"**
CS1024 Console **M5, P10H**
TD100 Switchboard **P10**
550, 501, 502, 507, 510 **J1, M1**
554, 564, 565, 576, 577 **"**
830, 835, 842, 854 **"**
2200, 2254, 2300 **NO**
2354 (1 line) **"**
8525 (2500 style) **M1**
501, 601 **"**
2500, 2502, 2554, 2564 **J1, M1**
2565, 2566, 2567, 2575 **"**
2576, 2577, 2830, 2831 **"**
2835, 2842, 2843, 2844 **"**
2854, 2870, 2871, 3554 **"**
2861 **"**

N.K.S. 131

2930 **M1**
900,2900 **J1, M1**
SKS-1 **J1**
SKS-2 **M5**
Multi-function II **J1**

Aries 308/616

Aries 2912,2926,2927,2928 **M1**
Trendline (Dial in Handset): **"**
8225,8275 (1 line) **NO**
Feature Phone: **"**

PC1008 (1 line) **M5**
3480,3482,3484 (1 line) **"**

Classic Set:
4525 (1 line) **M5**

Medallion (1 line):
2480, 2481, 2482 **M1**

Medallion (2 line):
2485 **"**

3485, 8575 **M5**

Citation (1 line):
2020, 2021, 2022, 2025 **M1**

Tribute (1 line):
2010, 2011, 2012, 2015 **"**

Tel-Trex:
398975-MDE-27M **NO**

Tel-Trex (1 line):
2980 **M1**

Tel-Trex II (1 line):
3980, 3981,3982,3983 **M5**

3984, 3985, 3989 **"**

ECS 56/136

Proprietary Sets **M5**

EKS 616

Proprietary Sets **M1**

EKS 308, 1664

Proprietary Sets **M5**

EKS 320

Console **"**

MILLENNIUM

ISDN Sets **"**
18 and 30 Button **^aM5**

^a Telset must be programmed for headset use. Consult Cortelco manual for programming instructions.

ALLEN TEL PRODUCTS, INC.

10/20/30 Line Panel Set **J1**
GB10716PB Series **"**

ALSTON

Tascon Console **P10H**

AMBI CORP.

Ambi Set **M1**
Ambi Terminal **"**

AMERICAN PHONE PROD.

Ameriphone RC3000 **M5**

AMERIPHONE

JV-35 **"**

AMTELCO

Eve System: **"**

Operator Station	^a P10	Attendant Console:	
PCMX		300A1-A, 301A1-A, 301B1-A	P10
Operator Station	"	510A; (3701-010)	^h M2
		510D; (3750-512)	"
		7101, 7104	"
		7102A	^h M2, ^a P10
		7103A (9497-002)	"
		7203H, 7205H	"
		7302	^h M2
		7303S (3176-16SA)	^h M2, ^b P10
		7305S (3177-40SA)	"
		7309	^h M2
		7403D, 7405D, 7406D, 7410D	^h M2, ^a P10
		7401D, 7404D, 7407D	^h M2
		7434D, 7444	"
		3178 NHL (2500 Style)	M5
		3100-ORD (500 Style)	M1
		3100-ITD (2500 Style)	"
		3178-SYS (2500 Style)	"
		3100-TJEB	M1, P10
		3100-TJEI (2514 Style)	"
		2500 MMGK (3101-ETR)	M5
		2500 YMGK	"
		Partner	
		MLS-6, MLS-12, MLS-34	^e M5, SP02
		Partner Plus	
		MLS-12D, MLS18D, MLS-34D	"
		System 2000	
		Proprietary Set:	
		CZP 880528, 880611	M5
		881014	"
		System 2600 (EKTS)	
		200 Set, 400 Set	^h M2
		Spirit 308/616 & 2448	
		Spirit 6 Button (6501)	M5
		Spirit 24 Button (6502)	"
		Definity 75/85:	
		Call Master 602	P10
		Call Master II	"
		Call Master III	"
		Call Master IV	"
		Definity G3V4	
		Call Master V	"H" Headset ^f
		Call Master VI	"
		Definity 75/85 5ESS-ISDN	
		ISDN Sets:	
		6504 (MBKU 10)	M5
		6508 (MBKU 30)	"
		7406, 7505, 7506, 7507	^h M2, ^a P10
		7514, 7516, 7526, 8102	M5
		8101, 8102	"
		8110	M5
		8403	^a P10, M5
		8410D, 8411D, 8434	"
		6408+, 6408D+	M5
		6416D+, 6424D+	"
ASPECT TELECOMMUNICATIONS			
All systems	M1		
ASUZI, LTD			
Pro 616, 1032			
Pro-616 Sets	M1		
Pro-1032 Sets	"		
Pro-XL 616, 1032			
Pro-XL-616 Sets	M5		
Pro-XL 1032 Sets	"		
SDX			
SDX Sets:			
FT-1, FT-2, FT-3, FT-4	M5		
AT&T/LUCENT/WECO/AVAYA			
Comcore (Trader Turret)	P10		
Central Office:			
Cosmic Frame	5		
660, 800 Test Board	P10		
(Communications Panel)			
VMC Console	"		
Switchboard Console:			
551, 557A/B	"		
Dimension			
100, 400, 600, 2000, 2000E			
CTS (MET Set)	M1, J3		
50B Console	M1, P10		
Horizon (ECTS)			
2991, 2992, 2993, 2994	M1, J3		
MET Set:			
836, 837, 2836, 2837	M1		
Com Key 416, 4A			
981A01, 2981A01	M1		
981A02, 2981A02	M1, J3		
981A03, 2981A03	M1		
983A01, 2983A01	"		
983A02, 2983A02	"		
2982R60	"		
Com Key 718, 7A			
7A/21A:			
832A, BM, CM	J1, M1		
2832A, BM, CM	"		
14A21A:			
833A, BM, C, CM, DM, EM	"		
2833A, B, CM, DM, EM, FM	J1		
System 80/5			
ACD Console	P10		
System 25,75,85			

^a If system has a non-amplified headset jack interface, P10H is required. Contact AmTelco at 1-800-356-9148 to make this determination.

6416D+M, 6424D+M	g	MMGT, YMGD, YMGJ, YMGK	"
8500 Series	M5, ^aP10	2511 HM	J1, M1
Attendant Console:		2514	M1, P10
302-A	P10	2515 BM	J1, M1
310-A1-03	"	2554 B, 2558 DM	"
Genesis		2563	J1, M1, P10
5 Button	^h M2	2564 HLM	J1, M1
10, 34 Button	^h M2, ^bP10	2565 HK, LK, LKMS, HKM	"
Merlin/Plus		2565 KKMS	"
206, 410, 820, 1030, 3020, 3070		2568 HAB, 2575 AM	"
5 Button Set:		2630/2631-D, -DA, -DA1, -DAM	"
(3160-111A)	^h M2	2634/2635 DA, DAM	"
10 Button (HFAl) Set:		2636 CA, CAM	P10
(3161-161A)	"	2637 DA, DAM	"
10 Button Set:		2660 A1M, 2662	J1, M1
(3161-172A)	^h M2, ^bP10	CS 2702 D, DM (Princess)	M1
34 Button Set:		2830/2831 A1M, CM	J1, M1
3162-417A, 3162-DISA	"	2851 CM, 2852 AM	"
34 Button (BIS) Set:		Universal Turret	M1, P10
3162-BISA	"	Touch-a-Matic Sets:	
Merlin II		310	NO
7313 (316510B)	"	870 A1M, A2M	J1, M1
7314 (316622B)	"	872 A1M, A2M	"
7316 (316734B)	"	960 A01M	"
7317 (3167DSD)	"	1600 (1 Line)	NO
7318	"	1662	J1, M1
BIS-19 (3165-10BA)	"	2870/2872 A1M, A2M	"
BIS-22 (3166-22BA)	"	2960 A01M	J1, M1
BIS-34 (3167-34BA)	"	5001/5011 T01A	^h M2
BIS-34D (3167-DSBA)	"	6000 (1 Line)	"
Merlin Legend		Consumer Products	
MLX Phones (MLX)	^c M5	Traditional 100:	
Merlin Magix		CS2500 DMGF (1 line)	M5
4424LD+ (4400-WLD)	^d M5	CS2554 BMPF (1 line)	"
4424D+ (4400-W24)	"	CS2500 DMGB (1 line)	M1
4412D+ (4400-W12)	"	Traditional 1000:	
4406D+ (4400-W06)	"	CS 2500 DMGH (1 line)	M5
4400D (4400-W0D)	M5	CS 2554 BMPG (1 line)	"
4400 (4400-W0N)	"	Feature Phone 1300:	
1A2		CS6401U01A 1 line	"
500 C/D, DM, FM	J1, M1	CS6402U01A 1 line	"
500 L/M, MM	"	CS6403U01A 2 line	M5
558 FM, 564 HD/HL	"	Feature Phone, 422:	
565 HK, LK	"	CS6500U09A (2 line)	"
568 HAA/MD, 575 AM	"	Feature Phone 400,410	"
585 HK, LK	"	412, 420, 530	"
630, 630DA	"	Feature Phone 460:	
631, 631DA	"	CS6500U03A (1 line)	"
635 DAM, 662	"	Speaker Phone: 480	
830/831 CM, DM	"	CS6500U01A (1 line)	"
851 CM, 852	"	Feature Phone:	
2500D, DM, DMG, MM, MMG	"	CS6601C02A	"
2500M, SM	"	620,700, 720, 730 (1 line)	"
2500 DMGC, DMGF, MMGB	M1	622 (2 line)	"
2500 DMGJ, DMGK, MMGJ	M5	Feature Phone 1600	"

CANDELA

Autotas ACD

Console **P10**

PBX Cardinal 30,60

Cardinal **M1**

C.D.T./COLONIAL DATA SERVICES CORP.

MP2000 (1 line) **NO**

AP1000 **M5**

AP2000 (1 line) **"**

AP2001 (1 line) **"**

AP2002 (2 line) **"**

AP3002 (2 line) **"**

CETEC VEGA

"Q" Plus wireless Intercom System

Master Station: QX-6 **NO**

CIDCO

CT100, CSD2400 **NO**

Beltpack: QTR-1 **"**

CISCO SYSTEMS

IP Telephone model 12+ **M5**

IP Telephone model 30 VIP **"**

IP Telephone model 7910 **"H" Headset^a**

IP Telephone model 7940 **"**

IP Telephone model 7960 **"**

^a Has headset port and you use a "H" series headset with a 26716-01 cord.

CLEAR-COM INTERCOM SYSTEMS

Master Station: MS-808 **1**

Main Station:CS-210,MS-200B **"**

Main Intercom Station: **"**

MS-400A **"**

Main Switchboard Station: **"**

SB-412A **"**

Remote Headset Station: **"**

MR-102A, MR-104A **"**

Remote Speaker Station: **"**

KB-111A, RM-120A, RM-400A **"**

Adapt-A-Comm System: **"**

Interface, AC-10K, AC-10H **"**

Wall Plate: WP-2 **"**

Beltpack:

RS-501, RS-502, RS-522 **"**

CMX COMMUNICATIONS

CKS 308/616/1648

Citation SST, EST **M5**

Citation **"**

CODE-A-PHONE

1050, 1350 (1 line) **M5**

1390, 1950, 1990, 3100 **"**

3200, 3350, 3390, 3450 **"**

3490, 3570, 4050, 4060 **"**

4150, 4290, 4350, 4650 **"**

6950, 7050, 7150, 7410 **"**

7420, 7650, 8100, 8150 **"**

2050, 2350, 8410, 8420 **NO**

Tel-A-Modem **M1**

8250, 8415 (2 line) **M5**

8425, 8440 (2 line) **"**

Intrepid: 308, 516 **"**

CAP 2650, 2670 (1 line) **"**

CAP 2690, 5890 (1 line) **"**

CAP 6250 (1 line) **NO**

Dial in Handset: **"**

CAP 1650 (1 line) **"**

6050,6650,6750 (1 line) **"**

COLBY

CTP730 **NO**

COMDIAL

500, 501, 508, 510 **J1, M1**

575, 502, 550, 551 **"**

552, 553, 554, 556 **"**

1654, 1704, 1705 **"**

1706,1716,1800,1810 **"**

Slenderet Phones (Dial in Handset): **NO**

0200, 0254 (1 line) **"**

2200, 2254 (1 line) **"**

2300, 2354 (1 line) **"**

S4220, S4230 (1 line) **"**

S4420, S4430 (1 line) **"**

S4320, S4330 (2 line) **"**

2500, 2501, 2502, 2503, 2507 **J1, M1**

2508, 2510, 2527, 2564	“	DSC Feature Phone	M5
2565, 2567, 2575, 2579	“	Voice Express:	
2550, 2551, 2552, 2553	“	VX-41B, C	M5
2554, 2556, 2800, 2816	“	Executech 308, 512, 616, 816, 824	
Image I: 2805, 2806	“	Executech: 3503, 3508	M5
Image II: 2830, 2831	“	3593, 3598, 6414	“
2835, 2842, 2843, 2844	“	Executech II 1432, 2232, 2264, 2296, 22128	
2851, 2854, 2861, 2864	“	Executech II: 3500, 3502	M5
2810, 2861, 2860, 2870	J1	3600, 3704, 3714, 3789	“
Century Phone (1900)	NO	3809, 3810, 3878, 3889	“
Business Phone 2000	M5	3910, 3979, 3989, 6509	“
Max Plus 3513, 3527	J1, M1	6579, 6600, 6614, 6620	“
3528, 3529, 3564, 3567	M1	6622, 6701, 6702, 6706	“
Max Plus (1-line)		6709, 6714	“
3525, 3579	J1, M1	Executech 2000	
3644, 3654	“	6016S, 6800S, 6814S	M5
3625: 079M, 907M, 900M	J1, M1	6820S, 6702X, 6720	“
909M, 979M	“	Access 2700 (1 line)	“
Max Plus (1-line)		Genie	“
3625: 493M, 961M, 970, 981M	M1	IMPACT	
3500, 3507, 3509	“	8012	M5
3779	M5	8024	^a M5
Max Plus (1-line)		DIGITECH	
3506, 3609, 3679	“	7000 Series	“
M Plus II (2 line)		UNISYN	
4500, 4507, 4509, 4579	M1	122S	M5
4625: 025M, 925M	“	^a Has headset port.	
4644: 970S	“	^b For Solo II phones the two black leads in the phone handset port may need to be reversed. Have customer call 804-978-2443 (Comdial Tech Support).	
4709, 4719, 4779, 4789	M5		
4909, 4979, 4989	“		
Americom 408, 816, 1632	M5	CONAIR CORP.	
ATC:		Prima: PR1001/PR2001	M5
ATC Impression:		PR6200 (1 line)	“
AT110, 111	M5	PR3001 (2 line)	”
ATC E-Z Comm: AT 206	“	CM200CS	“
DBX, UTX 1200, 5000		Standard Phones:	
Console	P10H	SW2502/350 2 (1 line)	M5
Max Key 3519	NO	TT2503 (2 line)	“
Max Key III 3513	M1	SW2450, SW2550, XS1202	NO
Max Key IV 3514 (3 line)	M5	SW202, SW205, SW1204	“
Executech Solo: 3522, 3523	“	SW2500	“
3582, 3583	“		
Solo II:		CONCORD	
5300, 5400, 5641	^b M5	612, 1024	
5500, 5521, 5531, 5631	“	Concord 6, 10	M5

AV 4/8, 8/16, & AV 32		T2001, T2002, T2003, T2004	"
AV16-X	"	Personal Terminal:	
		Exec: T2005	"
		Digital Phone: T2064	"
<u>CONSOLE SYSTEMS, INC.</u>		<u>CYBER DIGITAL</u>	
Microcom, MiniCom I/II	^a 2	CSX, MSX	
Centurion	"	Integrated Service Terminal	M1
		IST-12, IST-20	"
^a Some consoles may require 6-wire PTK-style headsets.		<u>CYGNET TECHNOLOGIES, INC.</u>	
<u>CONTEL- IPC SEE IPC</u>		CoSystem	M1
<u>CONVEYANT SYSTEMS, INC.</u>			
Centrex Console	M1		
<u>CORTELCO SEE ALCATEL</u>		<u>DAK</u>	
<u>CREST</u>		4000 AX	M5
CrestPhone II (2 line)	M1	5000 IRX	"
Tracer I (1 line)	M5		
Tracer II (2 line)	"	<u>DASH</u>	
		OPS	M5
<u>CRYSTAL TECHNOLOGIES</u>		<u>DATA PLUS</u>	
PhoneWriter	M5	ACD Console	M1
<u>CSE TELCOM</u>		<u>DATAVOX</u>	
Criterion 3x8		Datavox-One	M1
Criterion	M5		
Deluxe Station Set	"	<u>DAVID SYSTEMS</u>	
		Standard Set	M5
<u>CTG</u>		Standard Display Set	"
2500 e, t/a, (1 line)	M5	Executive Display Set	"
2e, f, 2f	"		
308, 612, 616, 816, 4080		<u>DAVOX</u>	
Proprietary Sets	"	DavoxNet	
1648, 3264		4900/5900 Workstation	M1
Proprietary Sets	M1	ST100 Auto Dialer	"
<u>CURTIS</u>		<u>DBA</u>	
Autodialer Speaker Phone	NO	208	
		Smartalk	M5
<u>CXC</u>		Smartcap	"
Rose PBX		<u>DEKA</u>	
Rose Attendant Console:		CD1600	NO
T1000	M5	CD1600M	^a M1
Rose ACD		EL400M, EL401M	"
Personal Terminal:			

HF400M, HF401M	"	DBA 706, 707	M1/M5
		DBC 531, 561, 562	M5
^a Deka E9020 Headset adapter required for on hook-dialing.		DBC 501/502	"
		DBC 601, 631, 661, 662	"
		DBA 180	"
		DFG 220-01, 222-01	"
		Model 100:	
		DBA 1033, 103	NO
		DBA 203	M5
<u>DELOS</u>			
2500, 2530	JS, M1		
<u>DIGITAL VOICE CORP (DVC)</u>			
Telenova I			
Telenova Station Set	M1		
Attendant Console:			
DBX1200/5000	"	<u>ESI</u>	
DVS Set	"	IVX Speakerphone	M5
DJ-2905 (1 line)	J1, M1		
		<u>EXECUTONE INFORMATION SYSTEMS</u>	
<u>DTI</u>		Command Key System:	
80/5		CBX816	
ACD Console	P10	Proprietary Set:	
		83010, 83011	M1
<u>DYNASCAN CORPORATION</u>		Compass Intercom K1700AV	NO
Cobra Phones:		Charter	"
ST401, ST610, ST620, RP710S	M5	K15100	J1
ST412, 8522	"	K15105	P10
ST500, 514 (1 line)	"	Command:	
AN8700	"	2056, 2612501, 2612503	M1
ST558, 600, 660, 662, 669	NO	E300	J1
Dial-in-handset		Gateway K21100, K21101	^a P10
ST510	NO	K21102, K21104	"
		X Trom II	M1
<u>EAGLE TELEPHONIES</u>		Equity I/II:	
Eagle Single Line	M5	K18020 thru K18028	NO
Eagle One, Eaglet:		Equity II:	
10, 20, 40, 60 Button Sets	M1	2522501, 2522502, 2522504	"
S.P.S., S-Class	M5	Equity III 308/512	
		2312501, 2312502	M1
<u>ENTEL CO.</u>		Encore 816/1232	
Console: UCX 3000	M1	2312504, 2512501	"
		2510502, 2512503	"
<u>ERICSSON INFORMATION SYSTEMS</u>		Encore 2464/3696	
ARD-561, 751 Console	P10	2512505, 2512506	"
ASB 102 Console	"	2512512, 2512513, 2512514	"
Prodigy +2		2512515, 2512516, 2512517	"
Console:		Encore CX (ECX) 408, 816, 1832, 3672	
7700-01, 7700-05	M1, P10	2992501, 2992502, 2992503	"
MD110/40, /90		2992504, 2992506, 2993506	"
MD110 Console	M1, P10H	SRX	
MD110 Set	M1		

S.R.X. Entrée:		ISDN Sets:	
100, 200, 400	"	SRS1050	M5
Vison Phone	M1	SRS270D, SRS2000, SR2000V	"
Elan 2080		Starlog	
Elan: 2882501, 2882502	"	CS10	M5
Vista I, II		CS20	"
Console	P10H	CT20	"
Enterprise		CSD	"
MLT Sets:		Starlog Console	M1, P10
E2602502, E2602503	M5	SBCS	M1
Isoetec:			
System 18 36 96 120		^a Requires Fujitsu modular adapter P/N 301848-01 and Fujitsu transition cable P/N 724139-02 for headset use.	
EZ-1/EZ-1 Genus	M5		
System 108/228		<u>FUTURA COMMUNICATIONS, INC.</u>	
Operators Integrated CRT	"	Futura/I-Tel 308, 616	
Digital Set: 82500, 82200	"	616	M5
82100, 82600, 82603A, 84600	"		
Agent Terminal: 84100	"	<u>GAI TRONICS</u>	
Model 12, 18, 32, 64	"	Cohort 3x4, 6x16, 12x48	M5
		Scope 3x4, 3x8, 6x16, 12x48	"
^a Requires Manufacturers jackset. Contact Executone for headset jack installation.		<u>GALAXY COMMUNICATIONS</u>	
<u>EXTROM</u>		DELTA 514, 616, 824, 1232, 2464	
Extrom II, HMS-616	M1	Galaxy Standard	M1
Extrom III, HMS-38	"	Galaxy Executive Display	"
Extrom IV, HMS-1032	"	TXE 1 Basic	"
612EE, 1032EE	M5		
<u>FUJITSU BUSINESS COMMUNICATION SYSTEMS</u>		<u>GENERAL ELECTRIC</u>	
Focus Hybrid 20, 50, 100		Mainfone	
Focus: HI5H, HI5D	M1	2-9100, 2-9116, 2-9166B	M5
Focus 196		2-9167, 2-9168A, 2-9230, 2-9270	"
Focus: ET10, ET11, ET20	M5	2-9280, 2-9285, 2-9315, 2-9320	"
Focus Digital PBX 960		2-9380, 2-9390, 2-9267A	"
Focus: ET1, ET2	M1	2-9400A, 2-9420A, 2-9435A/B	"
Console: 960	"	2-9223, 2-9266A, 2-9375, 2-9285D	NO
P/N 301-820-02	^a M1	2-9410NB, 2-9435C, 2-9220	"
Console 9600	M5	2-2910, 2-2950, 2-9432	"
Focus 9600		2-9375C	"
MLDT Sets:		Pro Series	
DT100A, DT100B	M5	2-9450A /B/C/D/E	^b M5
DT101B, DT200B, DT201B	"	2-9821, 2-9895, 2-9831A	NO
SST SET	P10	2-9981, 2-9985, 2-9316	"
ISDN		2-9630, 2-9892, 2-9980A/B	M5
		2-9438A, 2-9831A, 2-9632A	"
		2-9451	^c M5

HALLICRAFTERS

412

412 Set **M5**

HARRIS DIGITAL CORP.

Harris 20/20 L

Optic ACD Set:
780821, 780898 **M5**

Harris 20/20 PBX

Optic I, II, 4
20/20 Console **M1**

Harris D400/D1200 PBX

Attendant Console **P10H**

HARRIS LANIER

110 PBX

Precedent Telset **NO**

110 Attendant Console:
780-209 **"**

Attendant Console:
120-3990 **M1**

Easy Talk **M5**

Smartphone 7050 **"**

VIP, Classic, P130 **"**

Renaissance III, VI XII, XX & XXXII

EKT 201, 210, 220, 2201 **M1**

EKT 2205, 3102, 4010, **"**

4015, 4020, 4025, 4030, **"**

4035, 4044, 4045, 4047, **"**

4050, 4055, 5101, 5201 **"**

EKT 5010-5S, -SB **^aM1**

5015-5S, -SB **"**

5020-H, S, SD **"**

5025-S, SD **"**

5510-H, 5511-H, 5514-H **"**

5515-H, 5525-H **"**

EKT 5500-N (1 line) **M5**

Renaissance XII & XX

DSS Console **M1**

Renaissance XXXII

PBX Console **M1**

L-EKT-10, -10S, -20S **M5**

EKT 6200-N **"**

EKT 6510S, H **^bM5**

EKT 6520H, SD **"**

^a Headset must be plugged into headset port.

^b If telset has optional HHEU headset adapter, use switch position # 1.

HITACHI

EX10 PBX

ET616D **M1**

Inteliset I (MFT) **"**

Inteliset II (MFT) **M5**

HD100, 200 PBX

Inteliset 200 **"**

DX PBX

HD100 Attendant Console **P10**

HD200 Attendant Console **"**

HCX5300

Select Set: 200 (5051A), **M5**

300 (5052A), 400(5054A) **"**

500 (digital console), 700, 730, **"**

740 **"**

DT5054A

TURRET

6VLE TURRET **"**

CIP

2001, 2002 **"**

HOMACO

CDS-1, CDS-Mini 100 **P10**

HONEYWELL

Superswitch **P10**

Delta Plex 500 **M5**

DCX

Proprietary Set **"**

INFOGEAR

iPHONE **M5**

IPC INFORMATION SYSTEMS INC

64 IKS **J1**

EPC **"**

Centre Max I: 00895, 06088 **M5**

Centre Max II: 21608, 21610 **M1**

Series I Turret **P10**

Series II Turret **^aM5**

TradeNet I, II **M1, P10**

^a Requires use of Contel-IPC BT-327M adapter or Plantronics 18709-01 (modular-to-PJ327) adapter in conjunction with headset.

INTECOM

IBX S/10, 40, 80, 80+

Series A (G style handset):

ITE 12,15D, 21, 24D, 30 **M1**

Attendant Console-1 **P10**

Telari

Series B (K style handset):

ITE 4,12+ **M5**

ITE 12,12S, 24D **"**

STE Set (1 line) **M1**

Attendant Console-2 **"**

INTEGRATED TECHNOLOGY, INC.

CompuPhone (1 line) **M5**

INTEQ

824 **M5**

INTERDEX

T2-510 **NO**

INTERNATIONAL

1510 (Phone/answering machine) **M5**

INTER-TEL

Axxess **M5**

Keylux: **J1**

620, 1040, 1460 **J1**

MPK I, II

412T, 1032T **^a P10, M5**

SPK I, II

1664T, 2480T **"**

Phoenix, Hitec

412, 824, 1648 **M5**

616, 1232, 2480 **^a P10, M5**

GX 32/120

GX Sets **M5**

GLX 12

Executive Set **"**

GLX 308, 612

GLX Key phone **"**

GMX 408, 816, 1220

1628, 2036, 2440, 32120

GM Key phone **M5**

DVK phones **"**

550, 4500 **"**

KTS Exec **"**

^a P10: PLT 2 headset adapter from Intertel required

IWATSU AMERICA INC.

BT 1530,BT 2250,1530 **J1**

ET-126, ET-228 **M1**

Omega I: 714VC **J1**

Omega II: 1530/2250 **^a J1, M1**

Omega III: ET412, ET816 **b, "**

ET824, ET1632, ET2460 **"**

Omega IV: EX 816 **^c J1, M5**

EX824, EX1648 **"**

EX1232, EX2464 **"**

Omega IV:Superkey **^d J1, M5**

IDS 128 **"**

IDS Single Line, **M5**

Versaphone, Presidential **"**

Omega IV; EX 616 **^e J1, M5**

TXX616, TXX1648 **"**

ZT-D: 616, 824, 1632, 1232, 2464

Omega-Phone: **^f J1, M5**

ZT-6D/K, ZT-8D/K **"**

ZT-12D/K, ZT-24D/K **"**

ADIX

ADIX Button Sets: **M5, J1**

8,16,24,56 **M5, J1**

ZT-S 616

ZS-6KTS,-6KTD **M5**

^a JACKSET: Requires Iwatsu HJB adapter with Plantronics JackSet JSB200-1.

^b JACKSET: Requires Iwatsu HJA adapter with JackSet JSB200-1.

^c JACKSET: Requires Iwatsu SHSA-M adapter with JackSet JSB200-1.

^d JACKSET: Requires Iwatsu SHSA adapter with JackSet JSB200-1.

^e JACKSET: Requires Iwatsu SHCB-S adapter with JackSet JSB200-1.

^f JACKSET: Requires Iwatsu SHCB-Z adapter with JackSet JSB200-1. Also, M5: Require Iwatsu SMSA-Z adapter with headset for on-hook dialing.

		2010, 2011, 2021, 2031	M1
<u>ITT SEE ALCATEL</u>		^a Call Plantronics for adaptor cable.	
<u>JISTEL</u>		<u>LITTON</u>	
Console: 95,200,500	M1	E316, E324	M1
<u>J-TEC\TELECONNECT</u>		E316R	J1, M1
408\616:		714CX	J1
Proprietary Sets	M5	<u>LUCENT SEE AT&T</u>	
<u>KANDA TELECOM INC.</u>		<u>MACROTEL</u>	
616 Basic A & C	M5	Excel 308/816	
EK 616		308E, 816E	M5
616 Executive A & C	"	MT-16T	
EK 1232/2464, EKN 1232/2464		Proprietary Set	"
616 Executive Plus	"	MT-80D/MT-816H	
Tel-Basic	"	MT-12H, MT-14H, MT-16H	^a M5
<u>KEY SYSTEM U.S.</u>		MT-20D, MT-30T, MT-30X	"
Atlas II KSX 32, 128	M5	MT-207/308 Plus	M5
ET-4, ET-15, ET-36	"	MT-308/512/824	
ET-36D, ET-36OH, ET-36DOH	"	MT-3T, MT-3TX	"
Console	"	MT-5T, MT-5TX	"
<u>KS TELCOM</u>		MT-8T, MT-8TX	"
ST 24HD (Salta)	"	MT-1236/2464	
<u>LENOXX SOUND</u>		MT-12T, MT-12TX	"
PH321, PH322	M5	MT-16T, MT-16TX	"
PH300, PH306, PH308	NO	MT-24T, MT-24TX	"
PH310, PH312, PH315	"	MTX-128 PABX	
PH318, PH319, KB328	"	MTX Attendant Console	"
PH329, KB330, PH332	"	MTX Electronic Set	"
PH417, LX17	"	MTX Executive Display Set	"
<u>LEXAR BUSINESS SYSTEMS</u>		MTD-30E	NO
LX-1001		^a Phones may need modification for headset use. Contact Macrotel for information.	
LX 5, LX-15, LX-20	NO	<u>MEMOREX TELEX</u>	
LX-2	^a	Display Station	
LX-Attendant Console	M5	C19A, C078, C179	^a M5
1001L, M, S, VS		^a Headset must be plugged into headset port. If Display Station is strapped for carbon microphone, switch position 1 should be used. To convert to carbon microphone, call Memorex Telex	
TLX-2, -5, -15, -15HLS	^a	<u>MINDSET</u>	
TLX-Attendant Console	"	MS1202	M5
Lexar 2000			
LX 2000 Sets:			

<u>MITEL</u>		Mitrex Super Consolette	^a P10
SuperSet I, II	M5	T1600, T1602, T1603	"
Kontakt		T1604, T1605, T1606	"
Management Workstation	M1	T1609, T1617	"
Super 10		HT90	NO
Console	P10		
Teleset	^a		
SX-2, -5			
Teleset	^a		
SX 20			
Console	P10		
SX 50			
Console	M5		
SX 100			
SuperSet 3, 3DN	"		
Console	P10		
Generic 217 Console	"		
SX 200			
SuperSet 4, 4DN	M5		
SuperSet 420, 430	^b M5		
Digital Console	"		
Console	P10		
SX 2000, 2000VS			
SuperSet 7	M5		
Console	P10		
Super 1000 Console	M5		
Generic 1000, 1001, 1003	"		
1000 Console	"		
SUPERSET 4000			
4001	"		
4015, 4025, 4125, 4150	^c M5		
^a Compatible Headset Group determined by the model of the single line set used behind the system.			
^b On-Hook Dialing. Consult Mitel manual for programming instructions.			
^c Can use Polaris headsets and mute/hookswitch control switch.			
<u>MODULAR COMMUNICATION SYSTEMS</u>			
Mod-u-Com Console	^a P10		
^a May require 6-wire PTK style headset			
<u>MOTOROLA</u>			
STU III	M5		
Centracom I, II Console	SHS1963-01		
		Mitrex Super Consolette	^a P10
		T1600, T1602, T1603	"
		T1604, T1605, T1606	"
		T1609, T1617	"
		HT90	NO
^a Some Consoles require 6-wire PTK-style headsets. Use group 6.			
		<u>MURATA</u>	
		M700, M750, M4500	M5
		M1850	NO
		<u>NATIONAL TELECOM/SOLID STATE SYSTEMS</u>	
		ECD-16/Sts-16	
		2B/2C Consoles	P10H
		CEO PBX/ACD	
		ACDII Agent Set:	"
		SR 96/224/1000	
		ACD IV: 113-6064	M5
		Jr. Executive	
		116-6502, 117-6526	"
		<u>NBX CORPORATION</u>	
		NBX 100	
		Business Telephones	M5
		<u>NEC AMERICA, INC.</u>	
		Patrician Patti	
		T12-T, T24-T, T12-2P, T12-R	J1
		T24-R, 12-24	"
		Electra 411	
		EL411, ET-4T-2P, ET-4R-2P	"
		ET-4T-3P, ET-4R-3P	"
		600P	J1, M5
		Electra 28	
		ET 14-2, -3, -4, -5	J1, M1
		Electra 100	
		KeySet (ET20-1)	"
		Electra 616	
		ET6-1, -2, -3	^a J1, M5
		ET6-1P, -3P	"
		ET6H-1, -3	M5
		ET6H-1P, -3P	J1, M5
		Electra 1648	
		ET8-1, -2	J1, M1

ET16-1, - 2	"	ETW8-1, ETW16-1, ETW24	^h M5
ET16H-1	"	Electra Elite	
ET8-3, -4	M5	Dterm Series E	
ET16-3, -4	"	DTP-8, DTP-8D	^{i,j} M5
ET8-3P, -4P	J1, M5	DTP-16, DTP-16D	"
ET16-3P, -4P	"	DTP-32, DTP-32D	"
ET16H-3P, -4P	J1, M5	DTU-8, DTU-8D	"
ET16D-3, -4	"	DTU-16, DTU-16D	"
ET16H-3, -4	M5	DTU-32, DTU-32D	"
NEAX 1400			
1400 console: SN610	^b M1	^a JACKSET: Electra Telephone must be Revision 8 or higher for Jackset JSB200-1 hookup. Revision number found on the P.C. board inside of the phone.	
NEAX 2400			
Console 12,22,409,2400	P10	^b Switch on bottom of console must be set to "headset" side.	
NEAX 2400 ACD			
HAC610Z	"	^c JACKSET: D-Term 2 must be Revision A1 or higher for JackSet JSB200-1 hookup.	
HA750Z HDAC (N. America)	"	^d Requires NEC ADA -T ETU adapter with JackSet JSB200-1. Or JSB180-1 with Jackset By-pass.	
HA752Z HDAC (Australia)	"	^e Requires NEC ADA -E ETU adapter with Jackset JSB200-1. Or JSB180-1 and Jackset By-pass.	
HA751Z HDAC (Japan)	P10H	^f JACKSET: Requires NEC ADA -Z adapter with Jackset JSB200-1. Or JSB180-1 and Jackset By-pass.	
Electra IMS, Impulse			
Dterm 2:ETT1-1, ETT1-2	^c J1, M5	^g For Switch Hook control use NEC ADA Headset Adapter.	
Dterm 4:ETT 4-1	^d P10H, M5	^h Must use NEC ADA Headset Adapter.	
Dterm 4B:ETT 8-1	"	ⁱ Has headset port.	
Dterm 5:ETT 16-1	"	^j Can use the Polaris model of headsets.	
ACD Terminal: ETT16S-1	"		
Dterm 10:ETT-X-1	M5		
Dterm 500:ETT-D-1	"		
ISDN Dterm 3000			
ISDN: Dterm 3010	"	NICHO INC.	
NEAX 2400 IMS			
Dterm Series II:		1A2	
ETE-1HM-2	"	ITT 2564, ITT 2830	J1, M1
ETE-1-2, ETE-6-2	P10H, M5	NITSUKO CORPORATION	
ETE-6D-2	^e P10H, M5	1240/2470	
ETE-16-2, ETE-16D-2	"	Optima	M5
Dterm Series III:		NORSTAN	
ETJ-8-1, ET16DC-1	^f M5	All	M5
ET24DS-1	"	NORTHERN TELECOM	
Electra Mark II		500, 554, 564,	J1, M1
ETE6-1, ETE6D-1	^e P10H, M5	565, 2564, 2565	"
ETE16D-1, ETE16K-1	"	e Phone:	
Electra 8/24		QSQE 2500, QSFE 2500	M5
ETZ-16	M5	QSQE 2591, QSFE 2591	"
ETZ-16D	^f P10H, M5	QSKE 2500, QSKE 2554	"
Electra Professional		Logic I:	

QSK201, QSK2201	J1	Dial in Handset	
e Logic 1:		Silhouette: 8003-FWE-42	NO
QSQE/QSFE 2201FX	M5	Symphony 1000	"
e Logic 6:		Symphony 3000	"
QSHE 2206, QSFE 2206	"	Symphony 8000	"
Logic 10:		Symphony 5000	"
QSK200, QSK2200/3200	J1	Harmony: 8000FWE-01	M5
e Logic 10		Rapport, Rapport Plus	"
QSHE 2200, QSFE 220	M5	Quick Touch: 8001FWE-42	"
Logic 20:		Maestro: ISDN Set	"
QSK202, QSK2202	J1	Debut	"
Link Phone:		Pulse 120	
QSQE/QSFE 2201BX	M5	Agent Consoles:	
QSQE2500, QSFE2500	"	QCN100, QCN101, QCN102	P10
VICS		SM-1	
Unity (I) Basic Set:		QSU 63, 67	"
NT4L11AA/AD, NT4L11AD (8100)	M5	Meridian SL-1	
Unity (II) Link Set:	"	QSU6 (Canada)	"
NT4L12AA/AB/AC/AE/AF/AG (8200)	"	ACD SET: QSU7	^e P10
Unity (III) Business Set:	"	QSU1, QSU3	P10H
NT4L14AB, NT4L01AF	"	QSU60CFM, BQM, CQM	M1, P10H
NT4L01AH (8300)	"	QSU61CFM, BQM, CQM	"
Unity (VII) Handsfree Set:		Attendant Consoles:	
NT4L10AA/AD (8400)	"	QCW2, QCW3, QCW4, QCW5	P10
Unity 2-line Set:		Meridian Console:	
NT4L15AA/AC	M5	NT2GOOA-35 (M1250)	a
Unity Featured Set:		Meridian Digital Console:	
NT4L17AA	"	NT6GOOAA-35 (M2250)	a
Unity (XX) Controller Console:		Meridian SL-1	
NT4L14AA/AB, NT4L04AA/AB (8600)	"	QSU71 (M1009), (M1109), (M1309)	M5
Contempra:		NTZK06AA, AB (M2006)	"
QSK2100, 100, 110, 191 2110, 2191	NO	NTZK08AA, BA (M2008)	"
QSKE 2100, QSQE 2100	"	NTZK08AB, BB (M2008)	"
QSFE 2100	"	NTZK20AA, BA (M2016S)	"
QSK3500, QSK3564	J1, M1	NTZK20AB, BB (M2016S)	"
QSK3565, QSQM2500	"	NT1F07 (M2018)	"
QSQM100	"	NT1F06 (M2112)	"
Displayphone:		NT1F11 (M3000)	"
NT6K00, NT6K10	M5	NT1F05 (M2009)	"
Displayphone Plus:		NTZK16AA, BA (M2616)	"
NT6K07, NT6K90	"	NTZK16AB, BB (M2616)	"
Displayphone 220:		NT1F21 (M2317)	^d M5
NT1K00, NT1K02	"	M4020	M5
		M3901	"

Easy Touch (2 line) 22455	M5	Voice Express (Comdial) 100 (TIE, 612)	M5 “
Easy Touch: 22411	“	300 (Merlin 410,AT&T)	M2, ^aP10
PhotoTouch: 53011	“	400 (TIE, EK1232)	M5
Competitor: 21420	“	500 (ATI, Focus 50/100)	M1
Competitor Plus: 21410	“	700 (TIE, VDS)	M5
Competitor (2 line): 21430	“	Feature Phones:	
Techline Series:		FA4000, FA4100 (1 line)	“
2000, 24900	“	FA4200, FA4050 (1 line)	“
2700, 24910	“	FE5000, FE5100 (1 line)	“
2700S, 24920	“	FE5150, FE5200 (1 line)	“
2702S, (2 line)	“	FE5300 (2 line)	“
24930	“	Answering Phone:	
TM1552, 1300, 26500, 76500	NO	TA9100 (1 line)	NO
Integra 28, 38		Starline Phone (1 line/Dial in Handset):	“
Digitel; 78002, 78003	M5	PTP 1000, TR2202/2203	“
Integra 208, 412, 616			
Integra 75000	“	^a For P10, jack is AT&T adapter module 502A.	
Integra Executive 75005	“		
VariCom 28		<u>PACKARD BELL</u>	
76002, 77015	“	PB-FAX200	NO
^a If Telset has a date code ending with a letter A through D, use switch position # 1.		<u>PANADYNI</u>	
<u>OKI</u>		DID Switch	M1
Spectrum 100	M1	<u>PANASONIC</u>	
Attendant Consoles:		Eas-A-Phone:	
Spectrum 400, 700	P10	RC-TX91 (1 line)	M5
Discovery 3	“	RC-T350, 3I70 (1 line)	“
		RC-T420 (2 line)	“
<u>ORBACOM SYSTEMS</u>		Dial in Handset: (1 line)	
TDM-150 Console	^a P10	KX-T 2203, 2204, 2385	NO
		KX-T 3202, 3204 (2 line)	“
		KX-T 2010, (1 line)	M5
		2130, 2131, 2135, 2150	“
		2220, 2221, 2255, 2260	“
		2310, 2315, 2320, 2322	“
		2325, 2330, 2335, 2340	“
		2341, 2342, 2345, 2355	“
		2356, 2360, 2365,2390	“
		2410, 2415, 2420, 2421	“
		2422, 2425, 2427, 2429	“
		2432, 2475, 2620, 2622	“
		2630, 2632, 2634	“
		KX-T 2720, 2740, 2840	“
<u>ORIGIN</u>			
200 Voicephone	M5		
<u>PAC TEL</u>			
Standard Desk Phone:			
PB2500I-B (1 line)	J1, M1		
Standard Wall Phone:			
TR 2554 (1 line)	M1		
Basic 500/2500	“		
Basic Plus (TIE)	M5		
Smartset (TIE)	M1		

KX-T 2850	"	VA 41220, 41221, 41222	M5
KX-T 1450, 2155, 3110	NO	61420, 61421	"
KX-T3850	"	61422, 61423	"
KX-T 3120, 3122, 3130, 3135	M5	VA9200	
3142, 3145, 3150, 3155,	"	VA 9230	M5
3160, 3165, 3170, 3175,	"		
3204, 3250, 3280	"		
KX-TS 23W, KX-TS 25W	"	PANASONIC BUSINESS SYSTEMS	
KX-TS 400W, KX-TS 2020W	"	DBS 40, 72, 96	
KX-D 4130, 4985	"	VB-43210, 43220, 43221	^a M1
KX-F 50, 90, 100, 195	"	VB-43223, 43225, 43320	"
KX-F 500, 550, 850	"	VB-44225	"
KX-F 120, KX-F 230	NO	SDBS 308, 616	
KX-F 155, KX-FP 270	M5	VB-42210, 42211, 42212	M5
KX-F 3000, 3100	"	VB-42213	"
Panafax 135	NO		
KXT-D816	M5		
KXT-D1232	NO		
VA 8025, 8045 (1 line)	"		
VA 8070 (1 line)	M5		
VA 8100, 8120, 8130	"		
VA 8150, 8160, 8200	"		
VA 8205	"		
VA 8075 (2 line)	"		
VA 8020, 8030, 8035, 8080	NO		
VA 8085	"		
KX-TMC97-B	^b M5		
KX-TMC98-B (2-Line)	"		
KX-TSC50-B	"		
KX-TSC55-B (2-Line)	"		
KX-T308/61610			
30820, 30825, 30830, 30850	NO		
61620, 61630, 61631, 61650	"		
KX-T123211D			
KX-T 123210, 123220, 123230	M5		
KX-T 123235, 123250	"		
KX-T 7020, 7030, 7130, 7220	"		
KX-T 7230, 7235, 7425, 7434	"		
KX-T 96300B	"		
VA208, 309, 824, 1232			
VA 20820, 20821	NO		
VA 8400, 8405, 8465	"		
VA12020	M5		
VA12021, VA12022, VA30920	NO		
VA412, 614			
		PICTURETEL	
	"	SPH1	M5
		P.K.S.	
		516, 616	
		Executive Set	M5

^a Telset must be programmed for headset use. Consult Panasonic manual for programming instructions.

^b Telset has a 2.5mm headset port and can be used with our CHS or "M" series headsets.

PLANT EQUIPMENT

1A2

Standard 1A2 Consoles **^aM1,P10**

ComCentrex

Desk Consoles **M2**

Panel Mount **M1, P10**

ElectroKey

Desk Consoles **P10**

Panel Mount **P10**

Vesta **^bM5**

^a Some consoles may require 6-wire PTK-style headsets.

^b Use modular to plug-prong adapter PN# 18709-01

POLYCOM

SoundPoint Pro **2.5mm Jack**

POSITRON

304

301, 302, 304, 304S Turret **M1**

400

400L Turret **"**

IAP

600101 **J1**

PREMIER TELECOM PRODUCTS, INC.

Premier 8DEV T **J1, M1**

Premier 2500, 2554 **NO**

Premier 2530, 2541 **M1**

Premier 2572, 2575 (2 line) **"**

308, 616, 1648

Premier Keysets **"**

DHK

Premier LCD **"**

Premier Electronic **"**

1A3

1A3 Standard Set: NC612 **M5**

1A3 Speakerphone Set: NC612 **"**

ESP DX, 612, 1224, 2460, SLS

6/12

ESLI Single Line **"**

E-Set Single Line **"**

ESP 8, 12 or 24 button **^aM5**

ESP 12 or 24 BTN (display) **"**

FLAIR

6, 11, 21, 41 **M5**

SPRINT PROTEGE

Executive DKT **^aM5**

^a Telset can be programmed for on-hook dialing. Consult manual for instructions.

RADIO SHACK

Dial in Handset:

ET-120, -135, -272, -273, -275 **NO**

Contemporary Phone (1 line) **"**

43-527, -528, -529, -534 **"**

43-525, -526, -537, 538, -585 **"**

ET-283, ET-501, ET-290 **"**

ET-303, ET-273, 43-804 **"**

43-838, -830, -858, -833, -837 **"**

43-827, -834, -805 **"**

Duofone (1 line) **"**

TAD-242, -252 **M5**

140, 145, 146, 160 **"**

165, 166, 167, 169 **"**

173, 183, 185, 202 **"**

203, 205 **"**

170, 171, 175 **"**

12-1562 **NO**

ET-170, -175, -192, -600 **M5**

Radio Shack (2 line) **"**

ET-180, -181, -182, -191, -193 **"**

Duofone 195, 196 (2 line) **"**

System 205, 206 (2 line) **"**

Duofone System (2 line) **"**

202, 208, 210 **"**

Duofone system (4 line) **"**

404, 405, 406, 409 **"**

410, 411, 412 **"**

Duofone System 402 **M1**

1201/1202 **"**

1020 Phone/Fax **NO**

43-373A, 43-375A **M5**

RANDIX

PH316 **NO**

RAULAND

TC4204, TC4211 **M1**

RECORD A CALL

700, 1000, 2000 **NO**

2020, 3000, 3020 **"**

3060	"	120H, (61100)	P10H, M5
840, 1040, 2040, 3040	"	240H, (62100)	"
2140	M5	400H, (64100A, B)	"
		120EH, 240EH, 400EH	"
<u>REDCOM LABORATORIES, INC.</u>			
SBX-384/TRX/MBX/PSX			
Operator's Console	M1	300 SERIES 312	M5
Vodas, Vodas-K	"	600 SERIES 612, 624	^a P10, ^aM5
		Attendant Console	
		9208, 9224, 9225	M5
		9765	^b M5
<u>RING MEDICAL</u>			
Operator Panel	P10		
<u>ROCKWELL INTERNATIONAL CORP.</u>			
<u>ROCKWELL-COLLINS</u>			
Galaxy			
GVS D1, D2, D3, 3000, 050			
ISS-3000, ISDN 100			
Agent Consoles	P10		
<u>ROLLA ELECTRONICS</u>			
Agent Console	P10		
<u>ROLM</u>			
ETS 100	J1, M1		
ETS 100A	M1		
ETS 200	P10		
ETS 300	P10, M1		
Flashphone, Series 2500	J1, M1		
CBX, ACD, MCBX, VLCBX, VSCBX			
RP120, RP240, RP400	M5		
RP120H, RP240H, RP400H	P10H, M5		
RP400HD2	"		
Attendant Console:			
VXCBX-7900, 9755 ATC	P10H		
51001A, 87090A	"		
CBX118000, 9000AE, 9751			
Rolmphone RP244PC	M5		
Cypress Terminal			
Cedar	"		
Juniper I, II	"		
Redwood:			
120, (61000)	"		
240, (62000)	"		
400, (64000)	"		
<u>ROLODEX</u>			
		Telecaster 1000	NO
		Telemaster 2000	"
<u>RTS SYSTEMS INC.</u>			
Beltpack:			
		BP300	3
		BP320	NO
Console Mount Station:			
		CM300	3
Rack Mount Station:			
		RM300, RMS300	"
Portable User Station:			
		SPK300	"
Wall Mount Station:			
		WM300, WMS300	"
Master Station:			
		802	"
		810	"
Intercom Station:			
		824, 848	"
<u>SAMSUNG</u>			
Prostar			
		408, 612, 812	^a M5
		56EX, 120MX	"
		816+, 1224	"
DCS			
		LCD 24 BTN	M5

^a 600 series can use a Headset Recorder Options Module (HRO Module) from Rolm for on hook dialing using a P-10 or an M-10 or with an EHO option a Polaris headset may be used. Call Rolm at 1-800-835-7656

^b Requires Ackerman Headset Adapter from Rolm

SKTD4	NO	TP-200, -220, -250	"
		TP-270, -300, -320	"
		FO-220	"
		FP-700, -750, -800, -M62	"
		TP-300	"
		UX101, 103, 172, 254	M5
		UX265, 1000	"
		UX104, 105, 174, 305	NO
<u>SAN/BAR</u>			
Vision 2000	M1		
EX3100	M1, P10		
<u>SANYO BUSINESS SYSTEMS CORP.</u>			
TAS 155, 255 (Answering Machine)	NO	<u>SICENA</u>	
TAS855 (1 line)	M5	SHEILA	NO
1000, 1100	"	<u>SIEMENS</u>	
MD 3030	M5	SD-80, -192, 192MX, 232H	
MD3100 (1 line)	NO	Set 10, 30	M1
MD3300, 3400 (1 line)	M5	Console	P10H
MD3500 (1 line)	"	Saturn I, IIE, III	
AD100, AD200 (1 line)	"	Dyad, JR-Dyad	M6
AD400 (1 line)	"	Console:	
AD500 (2 line)	"	X5051-A878	P10H
ADX160, 260 (1 line)	"	40/80	
ADX360 (1 line)	"	34 Button EKT	M5
ADX460, 660	"	Euroset Plus Sets:	
EKS 6120, 6160		2100, 2101 (1 line)	M5
Station Sets:		2110, 2111 (1 line)	"
STN 1000, 1100, 2000,2100	M5	2210, 2212 (1 line)	"
		2220 (2 lines)	"
<u>SCOTT TECHNOLOGIES</u>			
Solo & Solo Plus	M1	816, 1224, 4080	
Stars & Westars	"	816 Proprietary Set	M5
		1224 Proprietary Set	"
		4080 Proprietary Set	"
<u>SEARS</u>			
SR1000	M5	HCM200	
SR2000	"	HCM 400 Set:	
SR3000, 34432	NO	12, 16, 24 Button	M5
34677, 34692, 34771	M5	OPTISET E	
		Standard	M5
		Entry	"
		HA+ option module	"
		CA or HA option module	^a M5
<u>SHARED RESOURCES EXCHANGE (SRX)</u>			
100, 200, 200S, 400	M1	GIGASET	
System One		2400	SHS1788-01 and 43038-01 adapter
Attendant Console:			
SRX 1000	M1, P10		
Vision Phone	M5		
<u>SHARP</u>			
TP-100, -150, -170	NO		

^a Can use the Polaris model of headsets.

		FC2552, FC2556, FC2560	"
<u>STC TELECOM. CORP.</u>		Business Sets: (2 line)	
Solitaire Plus Five	M5	FT300, 305, 325	M5
		FT350, 400, 425, 483	"
<u>SONITROL</u>		Answering Machine Phone:	
Sonitel 100	M5	FA460, 1200 (1 line)	"
AB1236	M1	FA1600, FA1625, FA1900	"
Telic T16	M5	FA955	"
XT2730183100	NO	FA965, FA1020	NO
		Feature Telephones: (1 line)	
<u>SONY</u>		FM 500, 500X, 550	M5
ITK300, ITM500, ITM602	NO	FM825, 850, 875, 1550	"
ITA500, 600, 650, 850, 4000	M5	FM2555, 3500, 3550	"
ITD100, 150, 250	"	FD8000, FD8100 (2 line)	"
ITB2, ITB3, ITB5	"	Business System:	
ITM10	"	FT383	"
ITM804, ITM850	"	FT412 (4 line)	"
		246 Key System:	
<u>SOUNDESIGN</u>		FS800, FS900, FS9000	"
Telephone 7278 (2 line)	M5	2465B Key System:	
Telephone 7255, 7267	"	FS900B Attendant Console	"
Telephone 7373, 7444	"	Concord AV8, AV32	
Slimline 7022, 7027	NO	Concord 10, 16	"
Clock/Radio Sets:			
7535, 7547	NO		
		<u>SOUTHWESTERN BELL TELECOM</u>	
<u>SOUTHERN TELECOM</u>		Matrix System	
SLT100 (1 line)	^a M5	Matrix Set: 24TDX, 36TDX	M1
SLT200 (2 line)	"	Focus Hybrid 20, 50, 100	
SLT300 (3 line)	"	Focus Sets	"
Caller ID	^b M5	STANTEL	
Classey 3100	"	SDX 60/180	
		Proprietary Sets:	
		FT-1, -2, -3, -4	M5
		Attendant Console:	
		Proprietary Set w/DSS	"
		Coronet	
		Coronet Sets: SS, HFS	"
		<u>SPECTRA MERCHANDISING</u>	
		DP-7	M5
	"	FP13M, FP23M, FP40M	NO
	"	TP9	"
		TL4-C, TL12 (Trimline)	"
	NO		
	"		

^a Headset port is standard on these models.

^b Headset port is optional.

SPRINT

SP 201, 202, 203
 SP 601, 602, 603
 SP 702, 705
 SP 802, 803, 804
 SP 9417-CW
 SP9516-CW

^a Has headset port.

STARTEL

ACD Console:

1200, 1500, 1800, 2050
 2700, 2800, 3700, 3710
 3720, 3730
 2800 w/80286 processor

STROMBERG CARLSON

2500 DM

Progress DKS

Keystation 4X12:
 6528, 6530
 Keystation 10X32:
 6532, 6534

Progress CDSS

Console

SUN MOON STAR GROUP

2500E

Solstar DKTS-Plus

EKTS KT-10II
 EKTS KT-48
 DKTS DK-80
 Feature Phone ST-30

TADIRAN

Emerald

EKT

Coral I, II, III

EKT 321
 VDK
 DKT, DST

TALTEK

747VA

TCO/ALCATEL/OPUS

Opus-20, -40, -80
 201, 203, 802, 803
 VDT 300
 CSF PQS 8002

TEC (Turret Equipment Corp.)

3000 Turret

TEC TEL

TSG 2500

TECHNICOM INTERNATIONAL, INC.

Businesscom I, II
 FPI Call Com
 CTX Managerial Set
 Basic Plus: 71350
 Custom Calling Set: 71325
 616 Set

TEKNEKRON INFOSWITCH CORP

Data Point
 Attendant console: 3970
 Electronic Set Infoswitch:
 6600

24/94

Key Set 24/94
 (94-3913-001)

CCMS/16

System Console & TSR

ACD86, & ACD86/DA

ACD Console 3901
 ACD Console 3911

Series I ACD

TTS (431-6122-105)

^a Use with 40287-03 adapter cable.

TELAMON-TECOM

KT510

T Com

Kelamon II, III & V

Telamon Set

M5
 “
 “
 “
^aM5
 “

GP 2
 “
 “
 P10

M1
 M5
 “

NO

NO

M5

“

“

“

M5

“

“

“

M5

M5
 “
 “
 “

M1

J1, M1

J1, M1

M5

“

“

“

“

P10

M1

M5

P10

^aM5, 4

“

P10

M1

M5

TELECO

UST1010DSD ^a M5
 UST1010DSK NO

^a Has headset port.

TELECOM TECHNOLOGY

ECD 4000

ECD Digital Sets ^a M1

ECD 1000, 2000, 4000

Single line sets ^b

ECD 6000

DDS Sets M1

^a Headset must be plugged into headset port.

^b Compatible switch setting is determined by the model of single line set used behind the system.

TELECOM, U.S.A.

408, 616

Standard Set:
 616012, 616013 M5

BCX 824/1236/2464

BCX Sets
 5 Button Set:
 15008 M1

8 Button Set:
 15110,15111,15112,15113 “

12 Button Set:
 15210,15211,15212,15213 M1

24 Button Set:
 15310,15311,15312,15313 M1

BCX BLF Sets
 8 Button Set:
 15117,15118,15517,15518 “

12 Button Set:
 15217,15218,15617,15618 “

24 Button Set:
 15317,15318,15717,15718 “

EXC 208/616/1232

ECX Sets:
 60007, 60010, 60011 M5
 60085, 60086 “

Challenger CM/CL

Challenger:
 38601,38602,38603,38604 “

TELECONCEPTS SEE TELEMATRIX

TELEDEX

MLT, -C, -E, -S ^aM5

SLT-1 “

Basic+, L2, P2, PL2 M5

SLT-2 “

ML-2, -P2 “

MLC-2, -P2 “

SL, -2 “

Diamond/Diamond+3 “

^a If Telset has a date code before 4/88 use switch position #1.

TELEDIAL

Feature Phone:

TDP-1000-1, -1SP M1

TDP-2000-1, -1SP “

TDP-4000 M5

Courtesy/Customer Service:

TDP-1000-8, -8PB, -13 M1

TDP-1000-18, -19 “

Secured Memory Phone:

TDP-1000-14, -14FP “

Restrictor Phones:

TDP-1000-3A, -5/6, -5A “

TDP-1000-6, -25, -26 “

Memory Phones:

TDP-100-2, -4A “

Flash Key and Basic Phones:

TDP-1000-7, -10, -12 M1

Dove-Phone: TDP-5000-1 “

Modemphone: TDP-3000-1 “

Data Sets: TDP-6000-1, -3 “

Triumph M5

TELEFONY & ELECTRONICS OF AMERICA

Tynamics

408, 812, 1024 M5

TELEMATRIX

Dial in Handset:

736022 (1 line) NO

172063, 176063 (1 line) “

592043, 596043 “

596073 (1 line)	“		
592053, 596053 (2 line)	“	<u>TELENOVA</u> SEE <u>DIGITAL VOICE CORP.</u>	
Capri:			
166043, 162043 (1 line)	M5	<u>TELEPATH</u>	
Metro Phone (1 line):		Talkback Phone	M1
TL-586043	NO	Amtron 416	M1, P10
Orion I:			
190543, 191543	“	<u>TELEQUEST</u>	
Signature I, II	“	Telequest 2600	M5
Sophisticate: 136043	M5	Grand Prix	“
Basic Wall:		433-SF	“
571546, 576046	“		
Standard Desk: (1 line)		<u>TELE RESOURCES</u>	
571542, 572042	NO	System 32, Gen 2	
572052, 574042	“	Proprietary Sets	M1
576042, 592052 (2 line)	“	System 150, 150S, 150E	
596052	“	Proprietary Sets	“
Deluxe Desk:			
576048 (1 line)	M5	<u>TELESCAN</u>	
576052 (2 line)	“	ACD Set	P10
2500 Premium:		EARTH NET	M1
576247	M1		
Intercom Phone:		<u>TELIM COMMUNICATIONS CORP.</u>	
272173	M5	Superb 1-SL:	
Feature Phone I:		1000-SL-00, 02, 04, 06	NO
016067	“		
Feature Phone II:		<u>TELKO INC.</u>	
016063	“	Dial in Handset:	
Feature Phone IV:		203,204,206,208 (1 line)	NO
016053	“	Fashion Phone:	
Feature Phone V:		403 (1 line)	“
036212	“		
Tele Matrix Sets: (1 line)		<u>TEL PLUS</u>	
100, 200, 300	^aM1	616, 1648, 3264	
Tele Matrix (2 line)		Proprietary Sets	M1
205, 208, 250	“	816, 4080	
250 DSS	NO	Proprietary Sets	M5
305, 308, 500 (3 line)	^aM1	MCM 200/400	
400 (2 line)	“	HCM Sets:	
508, 550 (5 line)	“	12, 16, 24 Button	M5
2700 MW (1 line)	M5		
		<u>TEL RAD</u>	
		Digital System	
		EX1, EX2, SD1, SD2	^aM5
		BA1, BA2	“
		Key Bx 812, 816	

^a Headset must be plugged into headset port.

BX Displayphone:		BLF Bus Com Plus Sets:	
83050-0100	M5	15017, 15117, 15118, 15217	"
1632, 2864		15218, 15317, 15318, 15517	"
83050-0000	"	15518, 15617, 15618, 15717	"
Key Bx Symphony		15718	"
Console:		DSO1	
73-00-1000, 73-00-2000	M1	Proprietary Sets:	
79-200-0007, 73-140	"	88661, 88662, 88663	M5
79-520-000	"	Ultracom, Meritor, EK820, 1236, 2260	
Symphony Sets:		I-, W-820, 1236, 2260	J1, M1
20, 24, 32 Button	M5	EK2464	M5
Single Line Set	"	EK2260 Executive Display	M1
Headset Station Displayphone:		Ultracom AT	
73430-0000, -0001	"	UAT Sets:	
DSS Unit	NO	3x8, 6x16, 12x24	^b M1
		32x64, 10832, 10864	"
		MXL64E	"
^a These phones have a headset feature switch.		EK416	
3COM		Delphi 4	M1
NBX		Paragon EK616	
3C10121	M5	Paragon (EK616)	M5
3C10122	M5	61650, 61655	"
		SmartSet:	
TIE		85100 (1 line)	M1
Turret		SmartSet Plus:	
Dealer Desk Turret:		85610 (2 line)	M5
T1030-2, -3	M1	100 HF	
T1060-2, -3, -4	"	E 100-C, E 100, E 80	J1, M1
T1220-2, -3, -4	"	S 100-C	NO
Command Key System: CBX816		2050T Key	
Proprietary Set: 83011	"	T 200-AT, -BT, -AR,	J1, M1
Bus Com I, II		T 200-BR, -AO	"
EK308T, EK516T	J1, M1	Execufone 2DX	M1
Bus Com III, IV, V		10T, 250B, 1030	J1, M1
Proprietary Set, TC8	M1	E200/201, AR/BR, AT/BT	"
Bus Com Select		E300C	J1
TC8DS	"	E300 CR, CT	J1, M1
Bus Com VI, VII		L200-A/B, S200/201	"
TC-12, TC-22	J1, M1	Custom Calling Set, 71325	M5
Bus Com Plus 308,512,824, 1236,2464		AP2002: 72002	"
BusCom Plus Sets:		Mercury: M1000	
15008, 15013, 15105, 15110	^a M1	M1000 Console	P10
15111, 15112, 15113, 15210	"	Digiphone:	
15211, 15212, 15213, 15310	"	28 button: 87730, 87731	M5
15311, 15312, 15313	"		

9-button: 87732	"	VDS	
M-Set: 87733	"	89050, 89053, 89054, 89055	"
TX250, 450, 2000		89058, 89060, 89061	"
TX Console	P10	Attendant Console	"
Feature Phone: 28 Button	M5	Ultracom, Meritor, Delphi:	
M-Group Set: Multi-line	"	EK818, 824, 1232, 1616	
M-Set	"	EK1648, 2464, TCX128	
Morgan		Multibutton: 86063, 86072	M5
Multi-button	"	86073, 86074, 86079	"
Executive Display	"	86082, 86089	"
Attendant Console	"	Multibutton Non-Display:	
Onyx		86050, 86070, 86080	M1
88155, 10 Button Set	"	Multibutton, Non-Display:	
88160, Set with 20 Button Module	"	86078, 86088	M5
88163, Set with 20 Button & Display Module	"	14 button, Non-Display:	
88363, Set with 20 Button & Display Module	"	86098	M1
EXEL 2		Four button:	
20160, 20180	"	86060, 86061, 86071	"
20161, 20181	"	One button:	
20162, 20182	"	86057, 86067	M5
EXEL 180 Console: 20150	"		
Meritor 1E		TMC	
60020, 60021	"	SOHO-M400	M5
Ultrakey		TMG	
60015, 60016	"	601-A1, 650-A1, 650-P	J1, M1
Econokey 1A2E		TONE COMMANDER SYSTEMS, INC.	
60025, 60026	"	Innovator II Console	M1, P10H
Delphi 6, 32		CTX5, CTX10, CTX20 Console	"
60030, 60031	"	CTX10, CTX20 Plus Console	"
60080, 60081	"	CentraCom 524, 532, 1030, 1560	"
Modkey 16, 32		CentraCom CPC600, 1000	"
60007, 60082, 60083	"	CentraCom CTX-200	"
Business Com 16, 12/32		CentraCom 30e-120	M1
60010, 60011, 60085, 60086	"		
DCX, Data Key		TOSHIBA	
88176, 89758, 89759	"	HDSS6560	M5
89760, 89761, 89762, 89763	"	Toshiba Com	J1, M1
89764, 89765	"	Attendant Console:	
Delphi Data Star		AATT102, DATT102, 8245G9	M1
88161, 88163	"	EKT 3600	"
DSO1			
Proprietary Set	"		

^a On-hook dialing with B-TB4-C card from TIE. Phone date code must be after 1/1/86.

^b On-hook dialing with C-HSU-A card from TIE.

Perception PBX		Altair III (2 line)	"
Strata III: EKT-102, -103 (Sets are non-modular)	J1 with P10H	SimTel II, III (2 line)	"
		SimTel IV, V (4 line)	"
Strata "S"		SimTel 100 (1 line)	"
MKSU 202,502	M1	SimTel (2 line):	
TSX-14, -16, -18	J1, M1	200, 210, 205 (ST-2)	"
Strata VI, XII, XX		208 (ST-4)	"
EKT 2101 through 2106	M1	SimTel (4 line):	
EKT 2201 through 2205	"	410, 412 (ST-4)	"
EKT 3101 through 3102	"	Message Minder 470	NO
Console	J1		
EKT single line	M5	UNICAL	
Strata "E"		LA PHONE	NO
EKT 6010, EKT 6015	^a M1		
EKT 6020, EKT 6025	"	UNICOM	
6000N	M5	110, 125	M5
DK 56/96		UNIDEN	
EKT 6510S, H	^b M1, M5	1010, 1015, 1020, 1030	M1
EKT 6520H, SD	"	1050	M5
EKT 7510H	"	1040, 8050	M1
DK 280		XE20, XE30, XE40, XE70	"
DKT2010, 2010H, 2010SD	^b M1, M5	EX4102	NO
2020S, 2020SD	"		
Fax Phone		UNISONIC	
4700	M5	6430, 6431, 9127	M5
^a Headset must be plugged into headset port.		9524, 6434	"
^b Switch position 1 can be used with Toshiba HHEU adapter. If HHEU adapter is unavailable, use switch position #5.		6750, 6772, 6900 (Dial in handset)	NO
TRILLIUM TELEPHONE SYSTEMS		UNITECH	
Talkto 109	M1	AFF20	M5
Talkto 208	M5	XK3500	NO
Trillium		UNIVERSAL TELECOM SERVICE	
Talkto 308, 616, 1032	M1	T126, T126-C	M1, ^aP10
Panther		^a For Headset Group 6: Jack is UTS Model 100.	
306, 612, 1032, 2064	M5		
Panther II		USX TELECENTERS	
306, 612, 1032, 2064	"	1010-BTS, 1010-SPK	^a M1
Trillium		1010-BLS	"
Talkto 1000 (1 line)	"	1020-BTS, 1020-SPK	"
		1020-LCD	"
TT SYSTEMS		EKT-O-Button	M5
Regal I (1 line)	M5	1240 PBX Console	M1
Regal II (2 line)	"		
Altair I, II (1 line)	"		

^a Headset must be plugged into headset port.

V-BAND SYSTEMS

VK-6030, 6060, 6090 **M1**
 VK6120, 6150 "
 Valent 10, 20, 30 **M5**
 VIAX Desk Phone "
 VIAX Console: "
 VK-7030 to VK-70240 "
 (30 Button Increments)

780, 787, 790, 797 "
 818, 1000, 1001, 1050 "
 828, 830 (2 line) **M5**
 758, 808, 810 (2 line) **NO**
 1100, 2001 (2 line) "
Key PBX/SPC
 7832, 7387 "

WESCOM

580 Console **J1, M1**
 80/5 ACD Console **P10**

VALCOM

V4500, V4600 **J1, M1**

WESTERN ELECTRIC (WECO) SEE AT&T

VIKING

308/715
 KT8 **M1**

WIN COMMUNICATIONS CORP.

Reliant 8, 16, 32, 50, 96 **M1**
 Reliant Displayphone **NO**
 Poets (Response):
 612, 1836, 3060, Exec ^a**M5**
 Marathon EKT "
 DSS/BLF Console **M5**
 100-D, 200-D Console "
 16D, MK1000 "

VOAD SYSTEMS

Keyboard Phone **M1**

VODAVI TECHNOLOGY

Starplus 2500, 4500 **J1, M1**
 Starplus: 2501, 2554 **M1**
 2601, 2602, 2603 **M5**
 2604, 2605, 2606 "
308, 612, 616, 816, 1224, 2448, 4080 "
 Proprietary Sets "
1648, 3264 "
 Proprietary Sets **M1**
1428, 2856 "
 Digital Sets **M5**

^a On-hook dialing can be achieved by installing a S.P.S.T. switch across terminals TLO and TLI of the phone's printed circuit board

WINDSOR

T1500, T3019 **NO**

WOLVERINE

Series 4000, A (4 line) **M5**
 Series 4000+, A+ (4 line) "
 Series 5000 (4 line) "
 Dial in Handset:
 Series 6000 (4 line) **NO**

WALKER

Clarity **M5**

WYSE

Terminal 60 (08030) **M5**

WANG INDUSTRIES

WI05
 SL 2500 **M1**
 Digital Work Station "

XTEL

Perfect 10 **M1**
 Status "

WEBCOR ELECTRONICS, INC.

708, 711, 718 (1 line) **NO**
 720, 721, 722, 737, 739 "
 740, 757, 759, 767, 768 "

ZAISAN, INC.

ES.1, ES.2 **M1**

ZOOM TELEPHONICS, INC.

TeleMagic

Zoom/Modem PC, ST, XT **NO**

ZTEL

PNX

Attendant Console **P10**

Z4, Z12, Z28 **M5**

ZETRON

4000 Series **See note ^a**

^a Consoles require Group 2 or Group 6 headset: see Appendix A.

APPENDIX A

Guide to Special Headset Groups

See page 1, *Using the Compatibility Guide* for instructions.

<u>H/S</u> <u>GRP</u>	<u>STARSET</u>	<u>STARSET NC</u> <u>NOISE CANCEL</u>	<u>MIRAGE</u>	<u>MIRAGE NC</u> <u>NOISE CANCEL</u>	<u>SUPRA</u>	<u>SUPRA</u> <u>BINAURAL</u>	<u>SUPRA NC</u>		<u>OTHERS</u>	<u>SERIES</u>	<u>NOTES</u>
							<u>NOISE CANCEL</u>	<u>BINAURAL</u> <u>NOISE CANCEL</u>			
1	SHS1720-01	-	-	-	SDS1008-11	-	-	-	-	-	-
2	SHS1963-01*	*	*	*	*	*	*	*	-	-	-
3	SHS1720-02	-	-	-	SDS1008-12	-	-	-	-	-	-
4	OH1002-1	-	-	-	-	OH5002-1	-	OH5002-1NC	-	-	-
5	SHS1471-01	-	-	-	-	SHS1473-01	-	-	-	-	PTT Model
6	SHS1890**	**	**	**	**	**	**	**	-	-	-

*H/S Group 2 is a SHS 1963-01 with any "H" headset top.

**H/S Group 6 is an SHS 1890-XX with any "H" headset top.

APPENDIX B

Cross Reference Chart

<u>Discontinued Headset Model Numbers</u>	<u>Old Group Codes</u>	<u>Equivalent New Technology (M10) Switch Settings</u>
MHB224-1 MHB424-1 MHB524-1 MHB525-1 MHB524-1NC MHB525-1NC	2	M1
MHB228-3 MHB428-3 MHB528-3 MHB529-3 MHB528-3NC MHB529-3NC	MHB224-1	M2
MHB230-1 MHB430-1 MHB530-1 MHB531-1 MHB530-1NC MHB531-1NC	3, 10	M5
MHB228-1 MHB428-1 MHB528-1 MHB529-1 MHB528-1NC MHB529-1NC	5	M5
MHB228-2 MHB428-2 MHB528-2 MHB529-2 MHB528-2NC MHB529-2NC	11	M5

<u>New Technology (M10)</u>	<u>Old Group #</u>	<u>Model Numbers</u>
M1	2	MHB224-1 MHB424-1 MHB524-1 MHB525-1 MHB524-1NC MHB525-1NC
M2	4	MHB228-3 MHB428-3 MHB528-3 MHB529-3 MHB528-3NC MHB529-3NC
M5	3, 10	MHB230-1 MHB430-1 MHB530-1 MHB531-1 MHB530-1NC MHB531-1NC
M5	5	MHB228-1 MHB428-1 MHB528-1 MHB529-1 MHB528-1NC MHB529-1NC
M5	11	MHB228-2 MHB428-2 MHB528-2 MHB529-2 MHB528-2NC MHB529-2NC

APPENDIX C

SP05/PLX500 Compatibility Information

PLX500: The PLX500 works with all M10 compatible phones.

The SP05 is compatible with all phones in the compatibility list with the exception of the following.

<u>Manufacturer</u>	<u>System</u>	<u>Model</u>	
ITT/CORTELCO	3100XL	237501 TLP, TSP	
	2300	Telset	
	801, 802	2801 thru 2806	
	501, 601	2861	
			299 Set
BELLSOUTH	STREAM LINE BASIC		
BITRONIC USA	ALL	All models	
COLONIAL DATA	ALL	All models	
CODE-A-PHONE	TEL-A-MODEM	8250, 8415	
	8425, 8440		
COMDIAL	VOICE EXPRESS	VX-41B, C	
	IMPACT	All models	
	DIGITECH	All models	
CONAIR CORP.	ALL	All models	
CONTEL IPC	CENTRE MAX II	21608, 21610	
	TRADENET	I & II	
DAK		4000AX, 5000IRX	
ENTEL CO.	CONSOLE	UCX3000	
ERRICSSON	MD110/40, /90	DBC 501, 502, 531, 561, 562, 601, 631, 661, 662	
	DDFG 220-01, 222-01		
FUJITSU	ISDN	SRS 1050, 270D, 2000 SR 2000V	
	STARLOG	All models	
GALAXY	ALL	All models	
GTE	OMNI SBCS	CS-10, -20, CSD	
	CONSUMER LINE	4250, 4275	
HITACHI	CIP	2001	
INFOGEAR		iPHONE	
INTER-TEL	ALL	All models	
J-TEC/TELECONNECT	408/616	All models	
KANDA TELECOM	ALL	All models	
MACROTEL	ALL	All models	
MOTOROLA		STU III	
NEC	ELECTRA 1648	ET16-3, -4	
	DTERM 2	ETT1-1, 1-2	
	DTERM 4, 4B	ETT4-1, 8-1	
	DTERM 5	ETT16-1	
	ACD TERMINAL	ETT16S-1	
	DTERM 500	ETTD-1	
	ISDN DTERM 3000	3010	
	NEAX 2400 IMS	All models	
	ELECTRA MARK II	All models	
	ELECTRA 8/24	All models	
		ELECTRA PROFESSIONAL	All models
	NORTHERN TELECOM	DMS 100 (P PHONES)	All models
	PHONE-MATE	PERFORMANCE	3950, 7050, 7350,

<u>Manufacturer</u>	<u>System</u>	<u>Model</u>
PREMIER	7650, 8250, 8450 PROFESSIONAL 1A3 ESP DX	6950, 7150 Standard set (NC612) Speakerphone (NC612) ESLI Single line E-SET Single line 8, 12, 24BTN TC4211
RAULAND		2140
RECORD-A-CALL		All models
ROLM	ALL	All models
SAMSUNG	ALL	EX3100
SAN/BAR		MD3030
SANYO		34677, 34771
SEARS		ITD100, 150, 250
SONY		FD8000, 8100
S.W. BELL	FEATURE PHONE BUSINESS SYSTEM 246 KEY SYSTEM KEY SYSTEM CONCORD AV8, 32	FT412 FS800, 900 2465B Concord 10, 16
STANTEL	ALL	All models
TADIRAN	EMERALD	EKT
TECHNICOM		EK616 PFT
TELECOM TECHNOLOGY	ECD6000	DDS Sets
TELRAD	KEY BX 812, 816 SYMPHONY SETS	83050-0000 20, 24, 32 BTN
USX TELECENTERS	DISPLAY PHONE PBX CONSOLE	73460-0000, -0001 1240