


ALINCO

DJ-X7

AM/FM/WFM
0.1-1299.995MHz
Wide Band
Communication Receiver



Antenna cap to cover connector



Curl-cable earphone/antenna comes standard

Fits right in a pocket, as thin as 14.5mm, as light as 103g!

SUPER audio. SMALL size. DJ-X7.

Catch the action on fire, public safety, traffic and many other frequencies, or just enjoy your favorite music and news on radio or TV stations with a receiver that fits in your shirt-pocket. When you hear the AMAZING audio quality, you might think you're listening to a high quality desktop scanning receiver. But the DJ-X7 gives you all those capabilities in a size and weight that makes it easy to take almost anywhere. Leading the way in miniature electronics technology with its revolutionary "credit card" size transceivers and multi-mode scanning receivers, Alinco sets a new standard for excellence with the DJ-X7.



AM/SW/FM/TV



Railways



Aviation



Amateur/
Commercial Radios



Cordless
Phone
(where permitted)



Transport



public safety



Highway
Maintenance



Navigation



Wireless Mic

...and many more!

Put the power of a desktop receiver into your pocket!



Actual ratio DJ-X7/Credit card

AM/FM/WFM 0.1-1299.995MHz
Wide Band Communication Receiver

DJ-X7T^{FC} DJ-X7E^{CE}

- "Credit card" size body weighing only 103g (3.62oz) fits right in pocket or purse
- Receives 100 kHz to 1.3 GHz*
- Triple conversion AM/NFM; double conversion WFM
- AM/FM/WFM modes selectable regardless of the frequency range
- 1,000 memory channels
- Easy to program with free downloadable software (optional cable required)
- Five operating modes: Preset, programmed, memory, VFO and tone scan
- Lithium ion battery-pack lets you operate almost a full day without recharging!**
- Three different antenna modes - earphone antenna, internal bar-antenna, and external SMA antenna; an optional external base-antenna is also usable.
- 39-tone Tone squelch
- Attenuator (approx 20dB)
- Auto-Power-Off
- Key-touch beep (on/off selectable)
- Battery-save
- Priority receive
- Monitor/Mute
- Memory-save
- Cable-clone
- Key-lock
- Pager (bell) function alerts you with a beep and an icon when a signal is received
- Standard adapter charges the Li-Ion battery AND operates with AC power (even at the same time, listening while charging).
- illuminated LCD
- Analog inversion scrambler decoding (available on E-version only)

* cellular frequencies blocked on T-version

** Operating times may vary subject to usage and settings

Specifications:

Receiver range : 0.100~1299.995MHz continuous (USA T-version cellular-band blocked 824.000~849.995MHz, 869.000~894.995MHz) **Mode :** A3E (AM)~F3E (FM,WFM) **Antenna Impedance :** 50 Ω unbalanced SMA-port **Operating battery voltage :** DC3.7V (external DC port DC3.7V~6.0V) **Current consumption :** Approx. 90mA average/Approx. 65mA stand-by/Approx 22mA battery-save on **Freq. Stability :** -7~+3ppm at -10c~+60c **Size :** 58W×96H×14.5Dmm(2.28W×3.78H×0.57D inches · w/o projection) **Weight :** 103g(3.62oz · antenna/battery inclusive) **Receiver :** Triple-conv. Super-heterodyne (NFM,AM) Double-conv. Super-heterodyne (WFM) **IF :** 1st/243.95MHz 2nd/39.15MHz (NFM,AM)/10.7MHz (WFM) 3rd/450kHz (NFM,AM) **Sensitivities :** Typical values in the bands, not the minimum guaranteed values FM/30~470MHz:-12dB μ(0.25 μV),470MHz or higher:-6dB μ(0.5 μV) 12dB SINAD WFM/76~470MHz:-2dB μ(0.8 μV), 470MHz or higher:9dB μ(2.8 μV) 12dB SINAD AM/0.1~50MHz:0dB μ(1.0 μV), 50MHz or higher:-8dB μ(0.4 μV)10dB S/N **Selectivity :** -6dB/12kHz or more -60dB/35kHz or less (NFM,AM) -6dB/130kHz or more -60dB/300kHz or more (WFM) **Audio Output power :** Max 100mW or more (8 Ω) **Typical operating time :** Approx. 19 hours with EBP58N (RX 1: Stand-by 4 BS-on)

• Specifications subject to change without notice or obligation.

• Cellular frequencies blocked on USA model. Unblocked versions available with proper documentation for authorized users only.

• Local regulation may apply to utility listening. Please check your authority for proper use.

Standard Accessories:

Instruction manual
Li-Ion Battery pack EBP-58N (3.7V 600mAh)
Adapter 6.0V 0.5A DJ-X7T : EDC-126 (120V)
DJ-X7E : EDC-128 (220V)
SMA whip antenna EA-131
Curl-cable earphone EME-25
Antenna cap

• Standard accessories may vary. Contact your dealer for details.



Optional Accessories:

Cigar-socket DC cable EDH-32 PC interface-cable ERW-4C
Straight-cable earphone EME-18 Softcase ESC-38

Authorized Dealer:

Copyright 2005 Alinco Incorporated, Osaka, Japan. All rights reserved. Although Alinco has designed this brochure to be as comprehensive and accurate as possible, we reserve the right to make changes at any time to our equipment line, optional accessories, specifications, or availability of any such device we manufacture and distribute. Please note that certain products and accessories may not be available in all countries of distribution. Please consult your Authorized Alinco Dealer for product availability and pricing.

ALINCO, INC. Electronics Division

Shin Dai Bldg., 9F
1-2-6 Dojimahama, Kita-ku, Osaka 530-0004 Japan
Phone: 06-4797-2136 Fax: 06-4797-2157
http://www.alinco.com
E-mail: export@alinco.co.jp