

X151X	Reset Lamp Timer For User	Others
X152X	Reset Lamp Timer For Factory	Others
X156X	Background color - purple	Others
X157X	Background color - black	Others
X158X	Background color - white	Others
X161X	Freeze - off	Others
X162X	Freeze - on	Others
X171X	Save current factory settings	Factory application
X172X	Load saved factory settings	Factory application
X173X	Load factory default	Factory application
X174X	Load all user default	Factory application
X175X	Burn-In mode off	Factory application
X176X	Burn-In mode on (for time limit)	Factory application
X177X	Burn-In mode on (for always)	Factory application
X178X	Load default for factory auto alignment procedure	Factory application
X179X	Save corresponding settings after auto alignment	Factory application
X180X	Burn-In mode on (for auto On/Off)	Factory application
X181X	Show Blue Filter	Others
X191X	Switch OSD language 1	OSD language
X192X	Switch OSD language 2	OSD language
X193X	Switch OSD language 3	OSD language
X194X	Switch OSD language 4	OSD language
X195X	Switch OSD language 5	OSD language
X196X	Switch OSD language 6	OSD language
X197X	Switch OSD language 7	OSD language
X198X	Switch OSD language 8	OSD language
X202X	Save as video color temp 1	Video color temperature
X203X	Save as video color temp 2	Video color temperature
X204X	Save as video color temp 3	Video color temperature
X205X	Save as video and data color temp 4	Video and Data color temperature
X206X	Save as video and data color temp 5	Video and Data color temperature
X207X	Load default of all video color temp. settings	Video color temperature
X212X	Save as data color temp 1	Data color temperature
X213X	Save as data color temp 2	Data color temperature
X214X	Save as data color temp 3	Data color temperature
X215X	Load default of all data color temp. settings	Data color temperature