

Camcorder / Wireless Microphone Configuration Chart

(*) Indicates discontinued model

CAMCORDERS				WIRELESS TUNERS				SUGGESTED WIRELESS PACKAGES			
CAMERA MODEL #	SUPPLIED MOUNTING HDWRE	OPTIONAL MOUNTING HDWRE (CAMCORDER)	WIRELESS RECEIVER POWER VIA:	AUDIO INPUT CONNECTOR TYPE	AUDIO OUTPUT CONNECTOR TYPE	COMPATIBLE UHF TUNER	SUPPLIED HDWRE	OPTIONAL MOUNTING HDWRE (TUNER)	PACKAGE #1 Hand-held	PACKAGE #2 Body-pack/lavalier	PACKAGE #3 Plug-on transmitter
HDCAM											
*HDW-700/1080 *HDW-700A HDW-750	V-wedge for Li-Ion batteries (Includes A8278-057-A bracket). HDW-750 has drop-in slot for direct installation of (1) WRR-855B tuner	Anton Bauer QR-SDH, w/ABWMK KIT adapter	WRR-855B-4-PIN 12V DC (w/BTA-801) WRR-810A, WRR-805A-internal "AA" batteries (x2)	XLR (X2).	BTA-801A, WRR-810A supplied XLR connector, WRR-805A-optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B-1/4 WAVE ANTENNAS (x2) WRR-810A-1/4 WAVE (x1) WRR-805A-antenna, soft case, 1/8" cable	BTA-801 (Include plate adapter) (REQUIRED for WRR-855A) X-0248-167-1, dual plate adapter required for WRR-805A	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)
HDW-F900									WRT-847B(CH) (transmitter), plus capsule	WRT-860A(CH) w/ECM-77BC lavalier microphone	WRT-808A(CH) (plus any dynamic hand-held mic)
BETACAM											
UVW-100B									WRR-855 or 861B(CH) (tuner)	WRR-855 or 861B(CH) (tuner)	WRR-855 or 861B(CH) (tuner)
PVW-D30	NP-1	BKW-L601 (INCLUDES A-8278-057-A bracket) -or- Anton Bauer QRSP-200A, w/ABWMK KIT adapter	WRR-855B-4-PIN 12V DC (w/BTA-801) WRR-810A, WRR-805A-internal "AA" batteries (x2)	XLR (X2).	BTA-801A, WRR-810A supplied XLR connector, WRR-805A-optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B-1/4 WAVE ANTENNAS (x2) WRR-810A-1/4 WAVE (x1), case, XLR cable WRR-805A-antenna, soft case, 1/8" cable	BTA-801 (Include plate adapter) (REQUIRED for WRR-855A) X-0248-167-1, dual plate adapter required for WRR-805A	WRT-807B(CH) (transmitter)	WRT-860A(CH) w/ECM-77BC lavalier microphone	WRT-808A(CH) (plus any dynamic hand-held mic)
PVW-D35									WRT-800A68 or WRT-807B(CH)	WRT-805B(CH) w/ECM-44BMP -or- WRT-822B(CH) w/ECM-77BC	Suggested microphones: F-740/9X F-780/X
BETCAM SP											
*BVW-300 *BVW-300A *BVW-400 *BVW-400A BVW-D600WS BVW-D600 PVV-3 *BVV-5		BKW-L601 -or- BKW-L403 (INCLUDES A-8278-057-A bracket) -or- Anton Bauer QRSP-200A/400A w/ABWMK KIT adapter	WRR-855B-4-PIN 12V DC (w/BTA-801) WRR-810A, WRR-805A-internal "AA" batteries (x2)	XLR (X2).	BTA-801A, WRR-810A supplied XLR connector, WRR-805A-optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B-1/4 WAVE ANTENNAS (x2) WRR-810A-1/4 WAVE (x1), case, XLR cable WRR-805A-antenna, soft case, 1/8" cable	BTA-801 (Include plate adapter) (REQUIRED for WRR-855A) X-0248-167-1, dual plate adapter required for WRR-805A	WRR-855 or 861B(CH) (tuner)	WRR-855 or 861B(CH) (tuner)	WRR-855 or 861B(CH) (tuner)
									WRT-807B(CH) (transmitter)	WRT-860A(CH) w/ECM-77BC lavalier microphone	WRT-808A(CH) (plus any dynamic hand-held mic)
			NONE						WRT-800A68 or WRT-807B(CH)	WRT-805B(CH) w/ECM-44BMP -or- WRT-822B(CH) w/ECM-77BC	Suggested microphones: F-740/9X F-780/X ECM-510
BETACAM SX											
DNW-7 DNW-9WS DNW-90 DNW-90WS DNV-5	V-wedge for Li-Ion battery Included. Built-in slot for WRR-855A	A-8278-057-A bracket (For 2nd WL unit only) -or- Anton Bauer QR-SDH w/ABWMK KIT adapter	WRR-855B supplied internally from camera 4-PIN 12V DC (w/BTA-801, FOR 2ND WL ONLY) WRR-810A, WRR-805A-internal "AA" batteries (x2)	XLR (X2) (For externally mounted WL unit ONLY)	BTA-801A, WRR-810A supplied XLR connector, WRR-805A-optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B-1/4 WAVE ANTENNAS (x2) WRR-810A-1/4 WAVE (x1), case, XLR cable WRR-805A-antenna, soft case, 1/8" cable	BTA-801 (REQUIRED FOR SECOND WRR-855A)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)
									WRT-847B (plus capsule) or WRT-807B(CH) or WRT-800A68	WRT-805B(CH) w/ECM-44BMP -or- WRT-822B(CH) w/ECM-77BC	WRT-808A(CH) (plus any dynamic hand-held mic) Suggested microphones: F-740/9X F-780/X
DIGITAL BETACAM											
*DVW-700 *DVW-700WS *DVW-707 DVW-709WS DVW-790WS	V-wedge for Li-Ion battery & A8278-057-A bracket included	Anton Bauer QR-SDH w/ABWMK KIT adapter	WRR-855B-4-PIN 12V DC (w/BTA-801) WRR-810A, WRR-805A-internal "AA" batteries (x2)	XLR (X2).	BTA-801A, WRR-810A supplied XLR connector, WRR-805A-optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B-1/4 WAVE ANTENNAS (x2) WRR-810A-1/4 WAVE (x1), case, XLR cable WRR-805A-antenna, soft case, 1/8" cable	BTA-801 (REQUIRED- Includes mounting hardware)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)
									WRT-847B (plus capsule) or WRT-807B(CH) or WRT-800A68	WRT-805B(CH) w/ECM-44BMP -or- WRT-822A68 w/ECM-77BC	WRT-808A(CH) (plus any dynamic hand-held mic) Suggested microphones: F-740/9X F-780/X

Camcorder / Wireless Microphone Configuration Chart

DVCAM											
DSR-130WS	NP-1	Anaton Bauer QRSP-200A w/ABWMK KIT adapter	WRR-855B- 4-PIN 12V DC WRR-810A, WRR-805A- internal "AA" batteries (x2)					BTA-801 (Include plate adapter)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)	WRR-855B(CH) (tuner)
*DSR-200 *DSR-200A DSR- 250	-	DSBK-201	WRR-810A, WRR-805A- internal "AA" batteries (x2)	XLR (X2) Not used for DSR- 300 and 500WS with WRR-855B / CA-WR855	BTA-801A, WRR-810A supplied XLR connector, WRR-805A- optional K-1334 XLR cable required	WR-855B (64, 66, 68) WRR-810A (64,66,68) WRR-805A (64, 66, 68)	WRR-855B- 1/4 WAVE ANTENNAS (x2) WRR-810A- 1/4 WAVE (x1), case, XLR cable WRR-805A- antenna, soft case, 1/8" cable	BTA-801 (Include plate adapter)	-	-	-
DSR-300 DSR-300A	-	CA-WR855	WRR-855A powered through CA- WR855 WRR-810A, WRR-805A internal "AA" batteries (x2)					CA-WR855	WRT-847B (plus capsule) or WRT-807B(CH) or WRT-800A68	WRT-805B(CH) w/ECM-44BMP -or- WRT-822B(CH) w/ECM-77BC	WRT-808A68 (plus any dynamic hand- held mic) Suggested microphones: F-740/9X F-780/X
DSR-500WS	-							CA-WR855 or BTA-801 / A- 8278-057-A			
*DSR-PD1	-	-	WRR-805A internal "AA" batteries (x2)	1/8" MINIPLUG- BALANCED	WRR-805A- Supplied 1/8" miniplug or optional K-1334 XLR cable	WRR-805A (64,66,68)	1/4 WAVE ANTENNA (x1), 1/8"-1/8" CABLE (x1), VINYL CASE	-	*SEE BELOW	*SEE BELOW	*SEE BELOW
*DSR-PD100 *DSR-PD100A	-	-	WRR-810A WRR-805A- Internal "AA" batteries (x2)	1/8" MINIPLUG- BALANCED OR XLR BALANCED (x1)	WRR-805A- Supplied 1/8" miniplug or optional K-1334 XLR cable	WRR-805A (64,66,68) WRR-810A (64, 66 & 68)	WRR-810A- XLR audio connector, antenna, case WRR-805A- 1/8"- audio CABLE , case	-	WRR-805A(CH) (Tuner) plus WRT-800A68 or WRT-807A(CH) (Transmitter)	WRR-805A(CH) (Tuner) plus WRT-805B(CH) (Transmitter) + mic (ECM-44BMP or ECM- 77BMP)	WRR-805A(CH) (Tuner) plus WRT-808A(CH) (Transmitter) + mic (F-740/9X or F-780/X)
DSR-PD150	-	-	WRR-810A WRR-805A- Internal "AA" batteries (x2)	1/8" MINIPLUG- BALANCED (x1) OR XLR BALANCED (x2)	WRR-810A- Supplied XLR cable WRR-805A- Supplied 1/8" miniplug or optional K-1334 XLR cable	WRR-805A (64,66,68)	1/4 WAVE ANTENNA (x1), 1/8"-1/8" CABLE (x1), VINYL CASE	-	SEE ABOVE	SEE ABOVE	SEE ABOVE
DV											
DCR-VX1000 DCR-VX2000	-	-	WRR-805A- Internal "AA" batteries (x2)	1/8" MINIPLUG- BALANCED	WRR-810A- Supplied XLR cable WRR-805A- Supplied 1/8" miniplug or optional K-1334 XLR cable	WRR-805A (64,66,68)	1/4 WAVE ANTENNA (x1), 1/8"-1/8" CABLE (x1), VINYL CASE	-	SEE ABOVE	SEE ABOVE	SEE ABOVE

1) *The WRR-855A with the BTA-801, WRR-810A and the X-0248-167-1, use the same mounting system. These are all compatible with camcorder models using the BKW-L601, DSBK-201, BKW-L403, NP-1, BP-90B and Anton Bauer adapters. However, whereas the WRR-810A operates on it's own internal battery power, the WRR-855A will ONLY operate with power received from the camcorder battery.

2) **The WRR-855A with the CA-WR855 adapter works ONLY with the DSR-300 & 500(WS). The WRR-855A with no bracket or adapter, works ONLY with Betacam SX models (plug-in slot).