

**MicroVerb 4****Product Description**

The MicroVerb4™ is designed to provide a wide variety of great sounding, easy-to-use effects for small studios, engineers and performing musicians. The key to MicroVerb 4's power is in its simplicity. It offers 200 programs that include everything from high-quality reverb, delay, chorus and flange to exciting multieffects and more. To customize your programs, two front panel knobs allow for quick, easy, user-storable edits, or use its MIDI inputs for control over program changes and modulation. You can then save your edited programs in the 100-space user program bank. Even though it's affordable and easy to use, the MicroVerb 4 offers the superb audio quality that you should expect from every Alesis processor.

**Specifications****Frequency Response:**

20Hz-22kHz +/-1 dB

**Dynamic Range:**

>90dB

**Harmonic Distortion:**

<0.009 @ 1kHz

**A/D-D/A Conversions:**

Conversion Scheme- 18 bit Sigma Delta

**Processor Speed:**

3 Million instructions per second,  
Processor Memory- 64K x 16 bit,  
Sampling Frequency- 46.875kHz

**Inputs:**

Number of Channels- 2, Nominal Level  
10dBV adjustable to +4dBV, Maximum  
Level +20dBV, +1-dBV  
Impedance 1M per channel in stereo

**Outputs:**

Number of channels- 2, Matrixed  
Stereo, Maximum Level +14dBV  
(Effect), +20dBV (Direct), Impedance  
500ohms

**Front Panel:**

Controls- Input Level, Mix Level,  
Output Level, Program Selection, Edit  
A, Edit B, Indicators- LED Display,  
Dual LED Meters

**Rear Panel:**

Jacks- Input Left and Right- 1/4",  
Output Left and Right- 1/4",  
Footswitch- 1/4" Stereo, MIDI In, MIDI  
Out/Thru Power- 5.5mm Barrel Jack

**Power Requirements:**

9 VAC, 5 Volt Amps external  
Transformer, UL and CSA Approved

**Dimensions & Weight**

**Dimensions:** 19"x1.75"x4" (WxHxD)

**Weight:** 2.6 lbs