

AMIS 215 EQ & 31EQ

2 Channel 15 Band Equalizer

The Australian Monitor Pro Series AMIS 215EQ is a single rack unit graphic equalizer. Featuring constant Q circuitry, selectable 6dB or 12dB slider range, balanced XLR, 6.35mm TRS & unbalanced RCA inputs & outputs, EQ bypass switches, ground lift switches, output level controls & overload LED's.

Single Channel 31 Band Equalizer

The Australian Monitor Pro Series AMIS 31EQ is single rack unit graphic equalizer. Featuring constant Q circuitry, selectable 6dB or 12dB slider range, balanced XLR, 6.35mm TRS & unbalanced RCA inputs & outputs, EQ bypass switches, ground lift switches, output level controls, overload LED's & variable high & low pass filters.

The features found in Australian Monitor Pro Series graphic EQ's are usually associated with equalizers many times the price of these. The AMIS 215EQ and AMIS 31EQ is an extremely well featured graphic equalizer at a contractor friendly price.

EQUALIZER

AMIS215EQ - 2 x 15 2/3 Octave ISO Spacing from 20Hz – 20kHz AMIS31EQ - 31 1/3 Octave ISO Spacing from 20Hz - 20kHz Type Constant Q Accuracy 3% Center Frequency Travel 20mm Positive Centre Detent Range +/- 6dB or +/- 12dB selectable

2. INPUTS

Type Active balanced/unbalanced Connectors 3 pin XLR, 6.35mm TRS balanced, RCA unbalanced Impedance 20k Ohms balanced, 15k Ohms unbalanced Max level +22dBm (level control at centre)

3. OUTPUTS

Type Active balanced/unbalanced Connectors 3 pin XLR, 6.35mm TRS balanced, RCA unbalanced Impedance <150 Ohms Typical Max Level +22dbm (2k ohms) +18dBm (600 ohms)

4. RFI FILTERS Yes

5. PASSIVE BYPASS SWITCHES Yes 6. OVERLOAD LED SWITCHES 5dB below clipping

7. LOW CUT FILTER (AMIS31EQ only) 10-250Hz, 12dB per octave 8. HIGH CUT FILTER (AMIS31EQ only) 3kHz-40kHz, 12dB per octave 9. FREQUENCY RESPONSE 20Hz-20kHz

10. IM DISTORTION (SMPTE) 0.005%

11. SIGNAL TO NOISE RATIO -94dB (20kHz noise bandwidth) 12. CHANNEL SEPARATION 50dB 13. COMMON MODE REJECTION

50:1

14. VOLTAGE 190-250VAC, 50Hz 15. DIMENSIONS* 1.75" H x 19.01" W x 8.50 D

16. WEIGHT* 5.51lbs

www.AustralianMonitor.com

AMIS 215 EQ & 31EQ





ABOUT

Australian Monitor Corporate Headquarters is located in Sydney, Australia. The organization has more than 20 years experience in the design and manufacture of audio amplifiers and associated products. They are a dynamic corporation, priding themselves on excellent customer service, better features and lower priced products for Sound Contractors and Audio Visual Integrators worldwide.



www.AustralianMonitor.com