



Electro-Voice®
a MARK IV company

Model FMK Flange Mount Kit

SPECIFICATIONS

Construction:

Cadmium plated steel. Mounting flange top surface finished in non-reflecting black

Hex Nut:

Wrench size 15/16 inch

Recommended For:

CP212 and CP218

Dimensions,

Height:

33.66 mm (1.325 in.)

Width:

38.10 mm (1.50 in.)

Net Weight:

80 grams (.198 lb)

Shipping Weight:

125 grams (.276 lb)

DESCRIPTION

The FMK flange mount kit is a permanent mounting accessory for the CP212 and CP218 podium microphone. The kit consists of a mounting flange, washer, nut, and three set screws, and is designed for installation into panel up to 3/4-inch thick.

Mounting a CP212 or CP218 is quick and easy using the FMK mounting kit.

INSTALLATION

1. Select the microphone location by first checking for obstructions under the panel that will interfere with the microphone and for a flat surface to properly seat the washer and retaining nut. Panel thickness may not exceed 3/4 inch.
2. Drill a 1 1/8-inch hole at the microphone location.
3. Set the roll-off switch on the microphone to the desired response.
4. Insert the microphone into the fixed mount adapter; secure by tightening the three set screws.
5. Insert the adapter into the drilled hole; secure this assembly with panel washer and retaining nut. Do not over-torque the retaining nut. Attach the microphone connector. For depth restrictions, a right-angle audio connector may be required.

WARRANTY (Limited)

Electro-Voice Accessories are guaranteed for one year from date of original purchase against malfunction due to defects in workmanship and materials. If such malfunction occurs, unit will be repaired or replaced (at our option) without charge for materials or labor if delivered prepaid to the proper Electro-Voice service facility. Unit will be returned prepaid. Warranty does not extend to finish, appearance items or malfunction due to abuse or operation under other than specified conditions, nor does it extend to incidental or consequential damages. Some states do not allow the exclusion or limitation of incidental or consequential damages, so the above exclusion may not apply to you. Repair by other than Electro-Voice or its authorized warranty service agencies will void this guarantee. A list of authorized service centers is available from Electro-Voice, Inc., 600 Cecil Street, Buchanan, MI 49107 (AC/616-695-6831); or Electro-Voice West, 8234 Doe Avenue, Visalia, CA 93291 (AC/209-651-7777). This warranty gives you specific legal rights, and you may also have other rights which vary from state to state.

Service and repair address for this product: Electro-Voice, Inc., 600 Cecil Street, Buchanan, Michigan 49107.

Specifications subject to change without notice.



ELECTRO-VOICE, INC., 600 Cecil Street, Buchanan, Michigan 49107

MANUFACTURING PLANTS AT ■ BUCHANAN, MI ■ NEWPORT, TN ■ SEVIERVILLE, TN ■ OKLAHOMA CITY, OK ■ GANANOCQUE, ONT
©Electro-Voice, Inc. 1990 ■ Litho In U.S.A. Part Number 531646-015

a MARK IV company