

Connecting the CO2E to other Manufacturer's Wireless systems

Manufacturer	Model	Connector	Pinout	Manufacturer	Model	Connector	Pinout
Audio Technica	ATW1031	Herosa HRS-4	1- Shield 3-white 4-red	Peavey	BPX	Switchcraft TA3F	1- white 2-shield and red 1- red
Beyerdynamic	TS-170	Lemo FG-331	1- Shield 2-red 3-white	Samson	TX-3	Hirose HR10-7P-6S	4-white 6-shield
	TS-190	4-Pin Binder #711	2- Shield 3-white 4-red	Sennheiser	SK-2012	Sennheiser/B&K Microdot	Ground- shield and red Center- white
		750 mono mini, 851 micro mini, Switchcraft TA4F, TA3F or 4-pin Lemo	1- Shield 2-white 3-red 4-jumper to pin 1				
Comtek	M-72, M72-B, M-182, M-82		1- red 3-white 4-shield	Shure	U-1 L-11	Switchcraft TA4F	1- Shield 2-red 4-white
Electro-Voice	MS-2500A	Switchcraft TA4F	1- Shield 2-white 3-red	Sony	WRT-23, WRT-820A	SMC-9	1- red 2-white 3 and 4-shield
HME	All Models	Switchcraft TA4F	1- Shield 2-red 5-white	Telex		Switchcraft TA4F or 4-pin Lemo	1- Shield 2-white 4-red
Lectrosionics	M-185	Switchcraft TA5F	1- Shield 2-red 3-white	TOA	WM-340U, WM-370	Mini phone plug	Tip-white Sleeve-shield and red
Lightspeed Technologies	BP200, BP300	Hirose HR10-7P-4S	1- Shield 3-white 4-red	Vega		Lemo 4-pin	1-white 2-red 4-shield 1- red
Nady	All Models	Switchcraft TA3F	1- Shield 2-red 3-white			Switchcraft TA4F	3-white 4-shield