## 4x1VB

## **4x1 Composite Video Switcher**






The  $4\times1VB$  is a high performance switcher for composite video signals. It switches any one of four signals to a single output.

## **FEATURES**

- High Bandwidth 400MHz (- 3dB).
- Video on BNC Connectors 4x1V has RCAs.
- Mechanical (Passive) Switching No power required.
- Compact Size Part of the Kramer TOOLS™ family of compact, high quality and cost effective solutions.



## **TECHNICAL SPECIFICATIONS**

 $\begin{array}{lll} \text{INPUTS:} & 4 \text{ video, 1Vpp/75}\Omega \text{ on BNC connectors.} \\ \text{OUTPUT:} & 1 \text{ composite or single component video,} \\ \end{array}$ 

 $\label{eq:toy_toy_toy_toy_toy} 1 \mbox{Vpp/} 75\Omega \mbox{ on a BNC connector.} \\ \mbox{BANDWIDTH (- 3dB):} \mbox{ 400MHz.}$ 

SWITCHING SYSTEM: Mechanical, Break-before-make.

DIMENSIONS: 12cm x 7.5cm x 2.5cm

(4.7" x 2.95" x 0.98", W, D, H).

WEIGHT: 0.28kg. (0.62lbs.) approx.
ACCESSORIES: Mounting bracket.
OPTIONS: RK-T1, RK-T3 rack adapters.

