4x4A

4x1:4 Stereo Audio Switcher






The 4x4A is a high performance switcher for stereo audio signals. It switches any one of four input signals simultaneously to four identical outputs.

FEATURES

- **S/N Ratio** 90dB.
- Level (Gain) Control.
- Compact Size Part of the Kramer TOOLS™ family of compact, high quality and cost effective solutions.



TECHNICAL SPECIFICATIONS

 $\begin{tabular}{ll} INPUTS: & Four audio stereo, $1\mbox{Vpp/33k}\Omega$ typical, \\ on $3.5\mbox{mm}$ mini phone connectors. \\ OUTPUTS: & Four audio stereo, $1\mbox{Vpp/22}\Omega\Omega$ typical, \\ on $3.5\mbox{mm}$ mini phone connectors. \\ \end{tabular}$

on 3.5mm mini phone on 3.5mm mini phone of 3.5

 S/N RATIO:
 90dB.

 CROSSTALK:
 - 79dB @ 1kHz.

 THD @ 1kHz:
 0.018%.

 2nd HARMONIC:
 0.002%.

 POWER SOURCE:
 12VDC 20mA.

 DIMENSIONS:
 12cm x 7.5cm x 2.5cm

(4.7" x 2.95" x 0.98", W, D, H).
WEIGHT: 0.28kg. (0.62lbs.) approx.
ACCESSORIES: Power supply, mounting bracket.
OPTIONS: Model VA-50P power supply with six
12VDC outlets. RK-T1, RK-T3,

19" rack adapters.

