



4x1 Video Switcher

4x1V

The Kramer 4x1V is a high quality 4x1 mechanical switcher designed for composite video signals and using RCA connectors. It accepts up to four inputs and allows the user to select any input to be routed to one output using buttons located on the side panel. High quality switching components are used to ensure minimal crosstalk and very high bandwidth. The entirely passive

design of the 4x1V eliminates the need for a power supply. Unselected inputs are automatically terminated via 75 resistors.

The 4x1V is part of the Kramer TOOLS family of compact, high quality, cost effective solutions for a variety of applications.



TECHNICAL SPECIFICATIONS

INPUTS:	4 video, 1Vpp / 75 Ω on RCA connectors.
OUTPUT:	1 composite or single component video, 1 Vpp / 75 Ω on an RCA connector.
BANDWIDTH:	400 MHz, -3dB.
SWITCHING SYSTEM:	Mechanical, break-before-make.
DIMENSIONS:	12cm x 7.5cm x 2.5cm (4.7" x 2.95" x 0.98"), W, D, H.
WEIGHT:	0.28 kg. (0.62 lbs.) approx.
ACCESSORIES:	Mounting bracket.
OPTIONS:	19" rack adapters RK-T1, RK-T3 (see pages 6.24, 6.25 for details).

TYPICAL APPLICATIONS

- Presentation and display systems.
- Rental and staging applications.
- CCTV and home theater applications.
- Compatible with SDI and any other high frequency signals.