



4x1 Audio Stereo Switcher + 1:4 Distribution Amplifier 4x4A

The Kramer 4x4A is a simple, high quality 4x1 audio stereo switcher and a 1:4 distribution amplifier. It accepts four audio stereo inputs, and distributes the selected input to 4 outputs. The machine uses 3.5 mm mini phone connectors, and is therefore perfectly suitable for PC-originated multimedia and presentation

applications. A 12V power supply is provided, but the optional VA-50P can power up to six Kramer devices requiring 12VDC. The 4x4A is part of the Kramer TOOLS family of compact, high quality, and cost effective solutions for a variety of applications.



TECHNICAL SPECIFICATIONS

INPUTS:	Four audio stereo, 1 Vpp / 33 k typical, up to 5.2 Vpp max. on 3.5mm mini phone connectors.
OUTPUTS:	Four audio stereo, 1 Vpp / 220 typical, up to 5.2 Vpp max. on 3.5mm mini phone connectors.
AUDIO BANDWIDTH:	100 kHz. -3 dB.
THD @ 1kHz:	< 0.018%.
2nd HARMONIC:	< 0.002%
MAX OUTPUT LEVEL:	5.2 Vpp (+7 dBm.)
S/N RATIO:	Better than 90 dB.
CROSSTALK:	-79 dB @ 1 kHz.
POWER SOURCE:	12 VDC 20 mA.
DIMENSIONS:	12cm x 7.5cm x 2.5cm (4.7" x 2.95" x 0.98"), W, D, H.
WEIGHT:	0.28 kg. (0.62 lbs.) approx.
ACCESSORIES:	Power supply, mounting bracket.
OPTIONS:	19" rack adapters RK-T1, RK-T3 (see pages 6.24, 6.25 for details).

TYPICAL APPLICATIONS

- Audio production and duplication studios.
- Multimedia and Presentation audio switching and distribution.
- Audio field production applications.