## VS-16N/A Protocol Codes

## 2-bytes protocol

Command	Hexadecimal	Notes
	Code	
Set Dwell	H0 Hxx	xx - dwell time in seconds. Changes from 81(1
Time		sec.) to E3 (99 sec.).
Switch to xx	H1 Hxx	xx – number of the input. Changes from
input		81(input #1.) to DA (input #90.).
Start Scanning	H2 H81	Always starts from the lowest enabled input
		number.
Stop Scanning	H3 H81	Always stops on the currently connected input.