



FREEKIE





FREEKIE

Add lighting control to your scratch, backspin, bend, drag, delay, brake, reverse and power down.

Freekie, a new concept in creative lighting control, features easy pitch and pan/tilt control for instant lightshow to music synchronization.

FEATURES

- Pitch fader allowing instant speed manipulation of lightshow
- Control up to 12 fixtures each with 12 channels
- Smart macro function for easy creation of circle movements
- Joystick for pan/tilt control
- Master intensity fader for all fixtures
- Audio control: built-in microphone or external control signal input
- Multi-purpose smoke and strobe buttons (customizable for additional DMX units)
- Assign names to individual banks
- Instant control of up to 24 shows via MIDI
- Set wait/fade times for advanced programming
- Followspot function: isolate any single fixture to work as joystick-controlled followspot
- High compatibility: control any DMX-intelligent light
- Extremely intuitive and easy to use

SPECIFICATIONS

Hardware

19" rack mount controller with 14 faders and blue LCD display
Suitable for fixtures using up to 12 DMX channels
Built in microphone or external audio input

Programming capacity

10 banks each with up to 12 shows (each show contains up to 10 scenes)
168 DMX channels

Programming facilities

12 groups of 12 channels can be programmed together or individually

Playback facilities

Direct access to all functions
Manual override of any fixture including smoke and strobe

Trig sources

Midi notes and program change
Sound (via internal microphone or external audio input)
Auto rate

Measurements

Power supply: AC9V/1A

Size

(L x W x H)
482 x 176 x 95mm
(19 x 7 x 4in)

Weight

2.8 kg
(6.2 lb)



Martin