

Start code = 0
Implemented from CPU software version 1.8

MAC 500 DMX Protocol



		MODE																																																					
		1	2	3	4	25					50					75					100					125					150					175					200					225					250				
L I G H T	1	closed				SHUTTER					STROBE					LOW PWR (E)	DIMMER PULSE					RANDOM STROBE					OPEN	RND PULSE	OPEN	RESET	OPEN	LAMP ON	OPEN	LAMP OFF*																					
	2	open				←					←					80	←					fast					128	open	close	*	208	217	218	227	228	237	238	247	> 5 sec. 248 255																
C O L O R	3	CONTINUOUS COLOR SCROLL (WHEEL 1)										STEPPED SCROLL										CONTINUOUS ROTATION					CH. 4 ALT																												
	4	CONTINUOUS COLOR SCROLL (WHEEL 2)										STEPPED SCROLL										CONTINUOUS ROTATION					RND COLOR																												
	Alternates function (enable on ch. 3) 67 colors: white, purple, pink, magenta, red, orange, yellow, green, cyan, blue, black																																																						
G O B O S	5	OPEN					INDEXED GOBO SELECTION										ROTATING GOBO SELECTION																																						
	6	GOBO ROTATION																																																					
	7	STATIC GOBO SCROLL (STEPPED)										STATIC GOBO SHAKE																																											
	optional	STATIC GOBO SCROLL (CONTINUOUS)										GOBO SHAKE					CONTINUOUS ROTATION																																						
E F F E C T S	8	FOCUS																																																					
	9	IRIS																																																					
	10	PRISM																																																					
P / T	11	FROST																																																					
	12	PAN																																																					
	13	PAN FINE (LSB)																																																					
S P E E D	14	TILT																																																					
	15	TILT FINE (LSB)																																																					
	16	PAN/TILT SPEED																																																					
	17	EFFECTS SPEED																																																					