

DM2050 3-CHANNEL DJ MIXER



Product Description

DM2050 is a compact, 3-channel tabletop mixer designed for today's turntablist, desktop, and aspiring DJ. Featuring steep 3-band EQ on every channel, a replaceable crossfader with reverse and slope control, a dedicated microphone input with 2-band EQ, and multiple input sources, this entry-level mixer is big on features and easy on the wallet.

Key Features

- Inputs for 4-6 lines switchable, 2 phono inputs, and a microphone
- Steep 3-band EQ on every channel with rotary frequency kills
- Dedicated microphone input with control for treble, bass, and level
- Replaceable crossfader with reverse and slope control
- Six segment LED display for monitoring signal strength
- Toggle for master and pre-fader listen (PFL) metering

DM2050 3-CHANNEL DJ MIXER

Specifications

| Inputs | |
|--|---|
| Line: | 10Kohm input impedance |
| | 80mV rms sensitivity for 0dB output |
| Mic: | 600 ohm input impedance unbalanced |
| | 1.5mV rms sensitivity for 0dB output |
| | 400mV rms max input |
| Phono: | 47Kohm input impedance |
| | 1.3mV rms sensitivity @1KHz for 0dB output |
| Outputs | |
| Line: | 7V rms max |
| Headphone: | 0.5W into 47 ohm |
| Distortion: | less than 0.05% |
| Signal to Noise Ratio (maximum output JIS-A weighted) | |
| Line: | >100dB |
| Mic: | >95dB |
| Phono: | >85dB |
| Frequency Response | |
| Line: | 20Hz-20KHz ±0.5dB |
| Mic: | 20Hz-15KHz ±0.5dB |
| Phono: | ±1dB except for controlled attenuation of -3dB @ 20Hz to reduce rumble and feedback |
| Channel Equalizer | |
| Bass: | +12/-35dB @20Hz |
| Middle: | +12/-25dB @1.3KHz |
| Treble: | +12/-20dB @15KH |
| Channel Fader Kill: | > 90dB @ 1KHz |
| Crossfader Kill: | > 75dB |
| Crosstalk: | > 80dB @ 1KHz |
| Dimensions | |
| Dimensions: | 9.6" x 12" x 3.6" (LxWxH) |