ViewSonic[®] NextVision[®] HD10 HDTV Tuner

PLUG AND PLAY HIGH-DEFINITION TV RECEIVER



Make your HD-ready TV a true HDTV.

Simply plug the NextVision HD10 TV tuner into your HD-ready TV and you'll be receiving over-the-air digital programming in no time. The HD10 provides **CLEAR RECEPTION** for the increasing number of high-definition and enhanced-definition TV signals available on local broadcast stations without additional subscription fees. Getting CD-quality sound right through your home entertainment system is easy with the **DOLBY DIGITAL AND MPEG** audio decoding. Add the NextVision HD10 to your HD-ready TV for true HDTV with no strings attached.



The HD10 makes any HD-ready TV a true high-definition TV.

Open up the free over-the-air world of HDTV programming

--- Easily turns your HDTV-ready TV or A/V monitor into a true HDTV.

Provides clear reception of high-definition and enhanced defintion TV signals available on local broadcast stations.

---->Bring high-quality Dolby digital sound to your home theater.

With Dolby AC-3 digital and MPEG audio decoding you can easily connect digital audio to your home theater surround sound system.

··· Receive ATSC over-the-air broadcasts.

Compatible with all 18 ATSC signal formats.

Compatible with any TV or high-definition display that features component, composite or S-video inputs.

···* Picture-in-picture capability.

See what you've been missing. Use the PIP capability to watch your favorite news station without changing the station from that award-winning movie.

--- Supports all digital TV output formats.

Displays content in both standard (4:3) and wide-screen (16:9) aspect ratios and supports 480i, 480p, 720p and 1080i signals.





ViewSonic® NextVision® HD10 HDTV Tuner

NEXTVISION HD10 TV TUNER

PLUG AND PLAY HIGH-DEFINITION TV RECEIVER



- 1. RF In (external antenna required not included)
- 2. Video In
- 3. S/PDIF Out
- 4. Audio In (left/right)
- 5. S-Video Out
- 6. Component Video Out (YPbPr)
- **7.** Audio Out (left/right)
- 8. CVBS Out
- **9.** DC In

VIDEO	Aspect Ratio Resolution Output Connectors Input Connector	4:3, 16:9 720x480i, 720x480p, 1280x720p, 1920x1080i Composite RCA jack, Component YPbPr – 3 RCA jacks, S-video, 4-DIN RCA for up-conversion, composite
AUDIO	Output Connectors	Analog – RCA, Digital – Coaxial
CONTROLS	Physical OSD RCU	Power (front panel adjustment) Program, EDIT channel, installation (manual setup, auto scan, quick scan), system (password, video setup, audio setup, caption style), profile (transparency, information) 32-key IR remote control, standby, volume +/-, channel+/-, navigation arrows (4), select, menu, exit, list, fav, V-format, Input, PIP, A. ratio, audio, info, CC, mute and 10 numbered keys
POWER	Type Input Output Consumption	Universal 90–264Vac, 47–63Hz 12/5 VDC, 2.0 A 34 W typ
OPERATING CONDITIONS	Temperature Humidity	32–104° F (5–40° C) 5–95% (non-condensing)
DIMENSIONS (W X H X D)		189mm x 43mm x 265m 7.4" x 1.7" x 10.4"
WEIGHT	Net	0.725 kg 1.65 lb.





ViewSonic Corporation's QMS & EMS have been registered to ISO 9001 & ISO 14001, respectively, by the British Standards Institution.



Connect the HD10 TV tuner to an HD-ready LCD TV, like ViewSonic's N2700w, to enjoy crystal-clear, high-definition TV without additional subscriber fees.



ViewSonic Corporation • 381 Brea Canyon Road, Walnut, CA 91789

Phone (800) 888-8583 or (909) 444-8888 • In Canada (866) 262-1967 • Fax (909) 839-7922 • SalesInfo@ViewSonic.com • ViewSonic.com

Specifications subject to change without notice. Selection, offers and programs may vary by country; see your ViewSonic representative for complete details. Corporate names, trademarks stated herein are the property of their respective companies. Copyright © 2004 ViewSonic Corporation. All rights reserved. [11742-018-05/04] HD10-2